
Pre-Operation

SPECIFICATIONS

Power Supply	AC 120,60Hz	
Rated Power	23W	
Operating Conditions	Temperature:14°F–104°F / -10°C–40°C	
	Humidity: < 85% RH	

PACKAGE CONTENTS



Part	Description	Quantity
Α	Control Panel	1
В	Outlet Cover	1
С	Upper Body	1
D	Decorative Ring	1
Е	Lower Body	1
F	Power Cord	1
G	Combination Filter	1
Н	Base Cover	1


Pre-Operation (continued)



NOTE: Do not start the air purifier until you remove the plastic packaging from the filter.


1 Removing The Base Cover

 Twist the base cover (H) counterclockwise and remove it.




? Removing The Plastic Packaging

□ Take out the new combination filter (G) and remove the plastic packaging.




3 Inserting The Filter

Place the unpacked combination filter (G) correctly back into the air purifier.



4 Closing The Base Cover

□ Close the base cover (H) and turn clockwise, making sure it is closed tightly.




Operation



1 Turning On The Machine

- Put the plug in the wall socket.
- □ Press (button to turn the air purifier on/off.



$\mathbf{2}$ Adjusting Fan Speed ${\$}$

- □ Turn the dial to the desired fan speed:
 - \square I = low speed
 - □ II = medium speed
 - □ III = high speed

3 Using Auto Mode

 On Auto mode, the fan speed will be automatically adjusted according to AQI level as below.

AQ Color	Blue	Green	Orange	Red
Speed Mode	Sleep	I (Low)	II (Medium)	III (High)
AQ Level	Very Good	Good	Unhealthy	Hazardous

4 Reading the AQ Light

 Press button, AQ light turns on, and AQ light indicator will display the color according to the air quality.

AQ Color	Blue	Green	Orange	Red
AQ Level	Very Good	Good	Unhealthy	Hazardous

5 Using Sleep Mode

- □ Press 🕓 to turn Sleep mode on.
- Sleep, Power and Timer indicators will be at half brightness while sleep mode is on. Tap Speed,
 Auto, AQ and Sleep buttons to exit from Sleep mode.



NOTE: Sleep mode will not work in Standby mode.

6 Setting Timer

Press to turn on the timer, and to cycle through timer options: 2 hours, 4 hours, 8 hours and off the timer.



NOTE: Pressing \circlearrowleft or unplugging the air purifier will cancel the timer.

Operation (continued)

7 Filter Reset Light

 When filter indicator () ilghts, it means that you should check the filter if it needs to be cleaned or replaced.

8 Memory Function

When the air purifier is turned off and plugged in, it will remember the previous fan speed.



NOTE: The filter's lifetime is based on your house air quality and usage time. Using the appliance in a humid environment will reduce the lifetime of the filter.

Care and Cleaning

FILTER REPLACEMENT

Filter Replacement Force Mode:

If needed due to local conditions or personal preference, you can replace the filter even if the filter icon does not come on. Follow the procedure below.

To Force Reset The Filter's Lifetime:

- \Box At the standby model, press and hold on (\boxtimes) button for 3 seconds, the icon (\boxtimes) light on.
- □ Press and hold '\(\sigma\)' button for 3 seconds again, the filter light turn off, then the reset is finished.