



## ▶BEFORE YOU INSTALL

WARNING! RISK OF ELECTRIC SHOCK. Incorrect installation could be dangerous or illegal multiple breakers may need to be de-energized for safe installation. Please call a professional electrician if you are unfamiliar or uncomfortable with electrical work.



## ►Install the 3-way Switch Kit



Step 1: Find the circuit breaker and turn off the power. Remove your old switches but do not disconnect the wires. Step 2: Wire your smart switch kit with the

3-Way wiring method. Then install and secure

Done ⊕aleax.gosund.com ♂ amazon alexa

How to ask Alexa to turn on/off Smart Switch

find the device named xxx...

First you need to set exact name for the switch on Go

sund app. If not. Alexa may tells you: "Sorry, I can't

You can say to Alexa "Alexa, turn on/off bathroom

switch", this command will help you to do the work.

What to do next:


→Close this window to discove devices you can with Alexa.

Done 

skills-store.amazon.com

both switches after the wiring.

### ► Warning and Advice:



## **▶**Wiring Instruction

1. Find the right electric box, Gosund 3way smart switch is designed to be installed in the line side box (the box with live in wire) a, choose the electric box which is relatively close to the fuse box

b. Live in wire has voltage, please use an electrical tester to verify it c. If you are still not sure, simply choose either

electric box to get started. Gosund app will help you detect the right electric box later. d. Note: For connecting with regular switches, Gosund 3way smart switch must be installed with live wire (in front of regular switch), if not, then the smart switch function won't work.

## ►Install the Gosund App

1. Search for Gosund App on App store /Google Play Store, or just scan the QR code below to download (For iPhone, you can use build-in camera to scan the QR code For Android you may need barcode scanner to do that. Please confirm the App icon before downloading.)

PS: You can also add this smart switch to smart life app directly if you already have it on your phone, it is compatible and works the same way.

2. Register an account and memories the password, enter your email address or your phone number, then obtain verification code to complete the registry.



## Connect with Your Cellphone

Requirements: 2.4GHz Wi-Fi condition at home

A: For Easy Mode Connection- Green Indicator Light Blink Quickly

--> Confirm that the smart switch is well installed --->Open Gosund app--->Choose the "+"symbol.



--> Confirm the light status on your switch and follow -->Make sure the indicator light is flashing slowly the App guide. and confirm it in APP; (If you don't see green light quickly blinking, press

On/Off button to reset) ---> Set a unique name for this smart switch, choose

R-AP Mode

"Fasy Mode".

lashes slowly:



-->Choose your 2.4G Wi-Fi and enter the password and confirm it in APP;

-->Tap "Connect now" and choose Wi-Fi hotspot named "SmartLife-xxx", then go back to Gosund

->Long press on/off button until the indicator light

-> Please switch to "AP Mode" if the connection fails in

---> First go back to the Add Device "+" interface, choose

Add Device Ap Mode

the AP Mode on the upper right corner.

Add Device

-->Wait till successful configuration and then tap "Completed".

Note: if the connection fails in "AP Mode", please check if your router is dual-band Wi-Fi. If it is

dual-band Wi-Fi, please enter the router management interface to split 2.4G and 5G Wi-Fi, and then connect 2.4G Wi-Fi.



# ▶Getting to Know Gosund APP




### Set timer/schedule ✓ Set device names

Note: edit the default names in this interface, for better management.

### ► Create Scenes/Groups

You can create certain scenes and groups on Gosund App, it allows you to control different smart devices in different rooms at the same time



If you want to give others the permission to control your smart plug, you can authorize that by device sharing function. Go to the Gosund app--> Choose the device you want to share-->Choose Edit Button -->Choose shared devices -->Add sharing-->Enter his/her Gosund account-->Search and complete.

## Add Gosund as a "Skill" for Alexa

for Gosund -->ENABLE TO USE-->Enter the Gosund account --> Authorize to use --> Choose Gosund. And then, the devices you added on will sync to Alexa App. You can also ask Alexa to discover new devices for you in this moment.



## ► Device Sharing

# ► How To Connect with Amazon Alexa

- 1. Amazon Alexa Device and Alexa App 2. The Smart Switch connected with Gosund App
- 3. Gosund App user ID and password

Open Alexa app and choose Skills&Games--> Search



### hings you can do with Alexa Voice Control the smart switch

Remote Control the smart switch via Alexa App Add the smart switch to certain groups on Alexa App For other questions about Alexa, please find out with Amazon Alexa support page, or contact us for help directly by email.

### Tips for using Alexa Voice Control

Please make sure the device name you set for the smart switch is unique and recognizable for Alexa

You should make sure all the smart devices names at your home are non-repetitive and recognizable

Vocie assistant system needs the exact command to do the work.

### ►How To Connect with Google Home You can do that by link Gosund app with Google

Home app, go to Google Home app and find "Works with Google" --> Search Gosund --> Enter your Gosund account --> Authorize to use. And then the Google Home App will guide you

hrough.

-14-

## Set up

Set up new devices or add existing devices

2. Open the electric box you choose, label the

wires as figure shown below. Normally, the live

wire is connected to the dark-colored screw

two traveler wires are connected to the two

yellow screws, neutral wire is the white wire,

3. Connect the 5 wires to the corresponding

wires of Gosund SW6, fasten them with the

to connect it to your home Wi-Fi.

provided wire nuts, then use the Gosund app

and the bare copper wire is your earth ground wire.

♠ Set up new devices Made for Google devices like C by GE smart

## Works with Google Have something already set up? Link your smart home services like Philips Hue and TP-Link

### ▶Trouble Shooting

## Q: Why my phone connection failed?

A:\* You should try both Easy Mode and AP Mode read page 6-page 8, make sure to follow the guide and try again.

\* Confirm your home Wi-Fi is 2.4GHz and you entered the correct password during the connection. \* Remove&Install the smart switch to start again

see what happens. Contact the after sales service for further help if you still have problems with the connection after following

-15-

### the stens above

### Q:Why can't I voice control it with my Alexa/Google? A:\* Make sure you set up smart switch successfully

on Gosund app, and they are working fine. \* Make sure you put correct account when you link Gosund as a skill on Alexa/Google App, and you can find it on your skills.

\*Make sure your Alexa/Google device is working

\* Check the device names that you set for this smart switch, it should be non-repetitive and recognizable for voice assistant, Also, please make sure your native language is available for Alexa.

If you still having trouble to voice control our smart switch after followed all instructions, do not hesitate to contact us for help.

### Q: Do I need to set up the device again if I changed my router?

A:Yes! you must set up the smart switch again if there is any change of the current Wi-Fi status, either you changed your router or your moved the device to a new house. However, you don't need to worry if you are just moving it inside your room, with the same Wi-Fi.

### Q: Why does it turns on/off or comes offline surprisingly?

### A:Check your Wi-Fi status and make sure the electricity is fine. Ccheck if you've set timer for it. If everything looks alright, just reset the smart switch on your app

again and see what happens. Email to after-sales services if this problem still exists

## ► Safety Information

his device is for Indoor&Dry condition use only Make sure the switch electricity is correct for the appliances that you attempt to use with. Do not try to disassemble this device by yourself be aware of product damage and safety risks.

environment. This device meets UL94 V-0 flammability standard.

Keep away from hot, humidity and other extreme

## ▶Warranty

90 days money-back guarantee:

If you're not satisfied with this purchase, you can choose to refund this order within 90 days.

## 12 months limited warranty:

\* Device was used in proper technical working condition. \* Covers unartificial failures and defections on this device.

-17-

### Risk of Damage:

Not suitable for appliances that exceed 15A Current, be careful.

Do not cover if the device was found artificial disassembled.

### Contact Us

For any inquiries or comments concerning our products, please send email to: service@gosund.com. Your advice is very much appreciated.

Shenzhen Gosund Technology Co., Ltd Website: www. gosund. com Email Support: service@gosund.com

