



Westinghouse

INNOVATION YOU CAN BE SURE OF

Consumer Guide

Inverter Generator Comparison

				
	Westinghouse iGen2200	Westinghouse 2400i	Honda EU22i	Yamaha EF2000iS
Engine Displacement	79 cc	79 cc	121 cc	79 cc
Rated Electrical Output	1,800 Watts	2,100 Watts	1,800 Watts	1,600 Watts
Maximum Electrical Output	2,200 Watts	2,400 Watts	2,200 Watts	2,000 Watts
Rated AC Electrical Voltage	240 Volts	240 Volts	240 Volts	230 Volts
240 Volt AC Socket Outlets	1	2	2	1
240 Volt AC Overload Reset	Engine Restart	Push Button	Engine Restart	Engine Restart
12 Volt DC Cig. Lighter Socket	No	Yes	No	No
USB Fast Charger Socket	Yes	No	No	No
Digital Hour Meter	Yes	Yes	No	No
Single-Sided Control Access	No	Yes	No	Yes
Dimensions L x W x H	50 x 29 x 45 cm	50 x 34 x 44 cm	51 x 29 x 43 cm	49 x 28 x 45 cm
Weight (Dry)	21 kg	20 kg	21 kg	20 kg
Fuel Tank Capacity	4.3 Litres	5 Litres	3.6 Litres	4.4 Litres
Fuel Level Gauge	No	Yes	No	Yes
Fuel Shutoff Valve	Yes	Yes	Yes	Yes
Run Time @ 400 Watts	10 Hours #	16 Hours	8 Hours #	10.5 Hours
Run Time @ 1,600 Watts	5 Hours ^	5 Hours	4 Hours ^	4.2 Hours
Noise Level @ 400 Watts (7 m)	52 dB(A)	52 dB(A)	Not Stated	51.5 dB(A)
Noise Level @ 1,600 Watts (7 m)	61 dB(A)	61 dB(A)	Not Stated	61 dB(A)
Warranty (Domestic Use) *	2 Years	2 Years	4 Years ^Δ	4 Years
Warranty (Commercial Use) *	1 Year	1 Year	1 Year	1 Year
Recommended Retail Price	\$1,299	\$1,599	\$2,349	\$2,349

* Conditions apply. # @ 450 Watts. ^ @ 1,800 Watts.

Δ To qualify, the generator must be serviced for the entire warranty period by an authorised dealer.

Source: Manufacturers' websites as at 16 January 2023.

2023-01-16

Power - when you need it - where you need it

westinghouseoutdoorpower.com.au

