



## Z-Wave Protocol Implementation Conformance Statement

# Z-Wave Plus In-Wall Smart Switch, White and Light Almond Paddles

## General Information

<b>Product Identifier:</b>	76591/ZWN4015
<b>Brand Name:</b>	Enbrighten
<b>Product Version:</b>	HW: 01 FW: 00.03
<b>Z-Wave Certification #:</b>	ZC14-23080317

## Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Electric Load Type</b>	Incandescent Inductive (e.g. Motor) LED
<b>Switch Load Capacity Current</b>	15A
<b>Color</b>	White

## Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

## Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico, US_LR, U.S. / Canada / Mexico, U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x3435
<b>Z-Wave Product Type:</b>	0x4952
<b>Z-Wave Hardware Platform:</b>	EFR32ZG23A
<b>Z-Wave Development Kit Version:</b>	7.19.3
<b>Z-Wave Library Type:</b>	Enhanced End Node 232

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Z-Wave Plus In-Wall Smart Switch, White and Light Almond Paddles, 800S

Association Group Information

Group # / Max    Description

Nodes

1 / 5

2 / 5

3 / 5

Supported Command Classes (17):

Association Group Information (AGI) V3	Association V2
Basic V2	Binary Switch V2
Central Scene V3	Configuration V4
Device Reset Locally	Firmware Update Meta Data V5
Indicator V3	Manufacturer Specific V2
Multi Channel Association V3	Powerlevel
Security 2	Supervision
Transport Service V2	Version V3
Z-Wave Plus Info V2	