

Product Specifications

Name	Automatic aroma diffuser
Models	S-AC-BT-AD-090-9/0
Size	6.61*6.61*2.75 inches
Material	PP
Volume	100ml
Amount of atomization	0.01-0.02ml/times
Atomization time	3s/time
Number of atomization	≥1500times/jars
Work cycle	From monday to sunday
Battery	4 pcs"AA" alkaline batteries / type-c 5.0v

※Remarks: 1. Under normal conditions 100M can be atomized 1500 times, the above-mentioned atomization amount and times are only reference values, different types of essential oils are different in the amount of spray, spray times are also different. 2. Product power can be viewed through the small program, low-power buzzer every 300 seconds to send a beeping alarm, and send low-power information to the small program.

The indicator light provided a prompt by flashing

Status	Prompt Method	LED Action
Power on	Blue LED	Flash twice, interval 2 seconds
Turn off	Red LED	Flash twice, interval 1 seconds
Reset the Password	Buzzer	The buzzer beeped for 1s
Reset Recorded Spray Times	Red/Blue LED	Red and blue leds flash alternately 3 times
Low Power	Red/Blue LED	Blue LED light 0.5s-off 2s-light 0.5s, total 60s
BLE Data	Buzzer	The buzzer beeps 2 times

Troubleshooting

Problem	Malfuction	Solutions
Not atomized or not working	a. Check if the battery is fully charged	
	b. Whether the machine is in a shutdown state	
	c. Check whether the atomizer head is blocked	
	d. Check if the oil bottle is loose	

Product maintenance

1. Machine Cleaning

a. Please use wet towel to clean the machine

b. Please turn off and take out the battery when cleaning the inside of the machine

c. If this product is not used for a long time, please clean the oil bottle and remove the battery

2. Clean the oil bottles and atomizer heads

a. Remove the essential oil bottle and unscrew the atomizing head

b. After washing the essential oil bottle, it is recommended to add an appropriate amount of alcohol and then reload it into the atomization equipment for improved performance and to eliminate any residual odors. Rinse the bottle again after this step and allow it to dry before using it again

Points to note

Attention Notes

After installation, please keep the machine vertical. Tilting or flipping the machine will cause oil leakage and result in damage to the machine.

Remove the battery when the machine is not in use for a long time.

Please do not immerse the equipment directly in water or wash it with water. Doing so can cause a short-circuit and result in damage to the machine.

Essential oil must not be mixed with debris or particles in order to avoid pipe blockages.

Do not alternate the use of different types of essential oils to avoid cross-contamination of scents.

Please keep the machine in a cool place and out of direct sunlight.

Keep the machine out of reach of children. Minors are advised to use the machine under adult supervision.

Do not disassemble, repair, or modify the machine, as this can cause product failure. For repairs, please consult your purchasing store or our customer service. (MEIDI_Service@meiditech.com)

Keep the machine away from fire.

Product Accessories

Legend	The name of the accessory	Quantity	Legend	The name of the accessory	Quantity
	User manual	1		T4.0X20mm screw	3
	Wall panels	1		Double-sided 3M glue	2
	Anti-theft screws	1		Essential oils bottle	1
	KA4.0 plastic expansion pin	3		AA alkaline batteries	4
	Type-C data line	1			

Product Warranty Instructions

We guarantee that our products meet the necessary safety standards and technical requirements and ensure that all product functions can be fully utilized through normal use and maintenance. Our company provides a one-year free warranty service for customers who have purchased our product (excluding consumables).

1. Within one year of purchase, customers can receive free warranty service if our maintenance staff confirms that the product failure is due to manufacturing processes or materials.

2. It will not be able to receive free warranty service if the product damage is caused by improper use, installation errors, modifications made by the customer, natural disasters, or other human-made damage.

FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications to this device not explicitly approved by manufacturer could void your authority to operate this equipment. This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

RF Exposure Information

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition, compliance with exposure requirements.

Artsun Enterprise Company Limited

Add: 19H Maxgrand plaza, No.3 Tai Yau Street, San Po Kong, Kowloon, HongKong

Golvvi

USER MANUAL

AUTOMATIC AROMA DIFFUSER

VO-1023G

Please read user manual carefully before using.

Product Description

Product Dimensions

Installation Instructions

1. Screw drilling installation:

2. No Drilling 3M Adhesive Installation:

※Note: This installation method is not suitable for rough or dusty walls.

Operation Steps

1. Add Aromatherapy Oil

2. Install the Battery

Open the battery cover, insert four AA alkaline batteries into the battery case, then place the battery case into the battery compartment, making sure that the two metal contact points are aligned with the positive and negative terminals of the battery case.

Softiny App Operation

1. App Download: Search for "Softiny" in the Apple App Store or Google Play Store, or scan the QR code below to download and install.

Scan the QR code to get the app from IOS store

Scan the QR code to get the app from Google Play store

2. Open the Bluetooth settings on your phone and the Softiny App. The app will automatically scan for nearby devices and connect to your phone.

1) Allow Softiny to access Bluetooth and location permissions

2) Select the device to connect and enter the Bluetooth connection password (Initial password is 888888) Note: If you forget the password, you can reset the device keys by pressing the button 5 times to restore the initial password.

3. Detail of the Equipment

1) You can view the current power level, location, and number of sprays. You can also test the spray, set a work plan, and perform other operations.

2) To configure the work plan: Click on "View Work Plan" and add the work schedule for the equipment. This includes selecting the cycle, start and end time, and spray interval time. Please note that no more than 8 work plans can be added.

3) To access equipment-related settings: Click on the "Settings" icon located in the upper right corner of the details page. This will take you to the settings page where you can make changes to the device name, and location information, reset the spray number, and device connection password, and other related operations.

4. About the System

On the Softiny App home page, click on the top button to view the current system version information and language settings.