



Z-Wave Protocol Implementation Conformance Statement

Open Close XS Sensor

General Information

Product Identifier:	ZSE41 800LR
Brand Name:	Zooz
Product Version:	HW: 02 FW: 02.00
Z-Wave Certification #:	ZC14-24020396

Product Features

Firmware Updatable	Updatable by Consumer by RF
Battery Type	CR2032
Battery Quantity	1

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico, US_LR, U.S. / Canada / Mexico, U.S. / Canada / Mexico
Z-Wave Product ID:	0xE001
Z-Wave Product Type:	0x7000
Z-Wave Hardware Platform:	EFR32ZG23A
Z-Wave Development Kit Version:	7.19.3
Z-Wave Library Type:	Enhanced End Node 232
Z-Wave Device Type / Role Type:	Notification Sensor DT / Reporting Sleeping End Node

(Continued)

Open Close XS Sensor

Association Group Information

Group # / Max Description

Nodes

1 / 5

2 / 5

Supported Command Classes (17):

Association Group Information (AGI) V3	Association V2
Battery	Configuration V4
Device Reset Locally	Firmware Update Meta Data V5
Indicator V3	Manufacturer Specific V2
Multi Channel Association V3	Notification V8
Powerlevel	Security 2
Supervision	Transport Service V2
Version V3	Wake Up V2
Z-Wave Plus Info V2	