• Android Connection Instructions:

1.Please open the power switch, blue lights up. Select the channel, press the Fn+C connect button, blue light twinkles.

2. Open "Settings" and then click "Connect"

3. Turn on Bluetooth to search for the pair name.

4. Click the pair name "Bluetooth 5.1 Keyboard", pair request is displayed, click OK.

5.There is a tip for connecting successfully, you can see your keyboard comfortably.

Remarks: After connecting successfully the next time you don't need match code, just open the Bluetooth keyboard power switch and the tablet PC "Bluetooth," The BT keyboard will search the device and automatic connects.

• Win 10 Connection Instructions:

1.Please open the power switch, blue lights up. Select the channel, press the Fn+C connect button, blue light twinkles.

2. Open settings, turn on Bluetooth, click Add Bluetooth or other devices.

3.Select "Bluetooth" in the Add Device to search.

4. You will find the "Bluetooth 5.1 Keyboard" and then click the pairing name to connect.

5.There is a tip for connecting successfully, you can see your keyboard comfortably.

• IOS Connection Instructions:

1.Please open the power switch, blue lights up. Select the channel, press the Fn+C connect button, blue light twinkles.

2.Open the tablet PC setting "Bluetooth" into searching and pairing status.

3.You will find the "Bluetooth 5.1 Keyboard" and then click to next step.

4.There is a tip for connecting successfully, you can see your keyboard comfortably.



Compatible System

Win /IOS /Android

Folding Bluetooth keyboard

User's Manual

Note: Please read the user manual carefully before you start using this product

Warranty Card

User information

Company or personage full name

_____

Contact address_____

TEL_____ Zip_____

The purchased product name and model NO.

_____

Purchased date_____

This warranty does not cover damage from accidents, misuse, improper operation, or any unauthorized modifications, alterations, or disassembly.

(1) Improper installation or maintenance, violation of product instructions or improper connection of power cutting wire.

(2) Or use unacceptable parts or open battery that are not provided by the company to include but not limited to improper wires such restrictions are prohibited.

Certificate

Inspector_____

Production_____

Keyboard Maintenance

1.Please keep the keyboard away from liquid or humid environment, saunas, swimming pool, steam room and don't let the keyboard get wet in the rain.

2.Please don't expose the keyboard at too high or too low temperature condition.

3.Please don't put keyboard under sun for a long time.

4.Please don't put keyboard close to the flame, such as cooking stoves, candles or fireplace.

5. Avoid sharp objects scratching products, timely to recharge products to ensure the normal use.

FAQ

1.The tablet PC can't connect the BT keyboard?

1) At first check the BT keyboard is into match code state, then open the table PC Bluetooth searching.

2) Checking the BT keyboard Battery is enough, the battery low is also lead to can't connect, you need charge.

2.The keyboard indication light always flashing when use?

Keyboard indication always flashing when use, is means the keyboard will be no power ,please charge the power as soon as possible.

3.The table PC display BT keyboard is disconnect?

The Bluetooth keyboard is not used for a period of time, the device will automatically enter the sleep state in order to save power, Press any key on the keyboard to wake up, and the Bluetooth connection will be automatically restored.

Multi-channel connection

- When connecting the first device, first press Fn+ BT1 and then press Fn+C to start the connection.
- Before connecting the second device, press Fn+ BT2 once, then press Fn+C to start the connection.
- Before connecting the third device, press Fn+ BT3 once, then press Fn+C to start the connection.
- To use multiple devices at the same time, press Fn + BT1 / BT2 / BT3 to switch to the connected devices freely .

Troubleshooting

Please contact the after-sales service.

Copyright

It is forbidden to reproduce any part of this manual without the permission of seller.

Safety Instructions

Do not open or repair this device. Do not use the device in a damp environment. Clean the device with a dry cloth.

Warranty

The device is provided with one-year limited hardware warranty from the purchase day.

Three system switching languages

IOS : control+Space key switch language

Windows : Alt+Shift switch language

Android : Shift+Space key switch language

Technical Specifications

Keyboard size: 304,31 x 96,12 x 9,86 mm (open)
152 x 96,12 x 18,83 mm (folding)

Key working current: < 3 mA	Weight: 218 g
Working distance: 6-10 m	Standby current: < 1,0 mA
Lithium battery capacity: 140 mAh	Sleep current: < 20 μA
Working voltage: 3,7 V	Sleep time: Ten minutes
Charger specifications: 5V⎓1A or 2A	Awaken way: Press key

Status Display LED

- Connect : Open the power switch, blue lights up, press the connect button,blue light twinkles.
- Charging : Indicator light will be on red, after fully charging, the light crush out.
- Low Voltage Indication : When the voltage is below 3,3 V, blue light twinkles.

Product features

iOS/Android		Windows		Windows	
Fn+	Corresponding function	Fn+Shift	Corresponding function	Fn+	Corresponding function
100%	Return to Desk	100%	Home Page	100%	Esc
1	Search	1	Search	1	F1
2	Select	2	Select	2	F2
3	Copy	3	Copy	3	F3
4	Stick	4	Stick	4	F4
5	Cut	5	Cut	5	F5
6	PrevTrack	6	PrevTrack	6	F6
7	Play/Pause	7	Play/Pause	7	F7
8	Next	8	Next	8	F8
9	Mute	9	Mute	9	F9
0	Volume+	0	Volume+	0	F10
-	Volume+	-	Volume+	-	F11
=	lock	=	lock	=	F12

Three system input method switch

IOS: control+ Space key Windows : control+ Shift

Android : control+ Shift