


SKMEI 1672 Operation Manual




(S) key MODE/ SET

FEATURE


- ★ 24H time display (LED display)
- ★ body temperature measurement (LED display)




Time Display



Normal
Temperature



Abnormal Temperature
(the left symbol flash
quickly)



Charging (the left
symbol flash)

1、Time display

- ★ press S key to display the time, it automatically turns off to save electricity when operation.

2、Time setting

- ★ Under the mode of time display , keep pressing S key for 5 seconds to enter the setting of “Hour” then press S key again to modify the number of “hour”. Press S key and hold it for 5 seconds again to enter the setting of “ minute” then press S key to modify the number of “minute”.

3、Test the temperature

- ★ Under the mode of time display, press S key to measure the temperature and the symbol °C flashes , symbol °C stop flashing after test finished.
- ★ Attention: There are 2 abnormal results of measurements when the temperature is out of the range of 32°C~42.5°C: ①LO or HI means it too low temperature or too high temperature to be out of range of measurement.② Red light will flash when temperature exceeds 37.5°C 。 Within range of measurement.
- ★ Measuring range is 34°C~42°C . Results of measurements will be affected individual difference, environment , clothing ,strenuous exercise and other factors . The result are for reference only and cannot be used as a basis for diagnosis .

Remarks: Wear your watch for ten minutes before detecting your body temperature;

4、Charging

- ★ Take off wrist band and connect it with USB charging cable
- ★ Led screen display : On charging : The left symbol flash
Full charge : The left symbol stop flashing.