



## Z-Wave Protocol Implementation Conformance Statement

### Mini Smart Plug

#### General Information

<b>Product Identifier:</b>	MP21Z
<b>Brand Name:</b>	Minoston
<b>Product Version:</b>	HW: 255 FW: 1.255
<b>Z-Wave Certification #:</b>	ZC10-20086962

#### Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Electric Load Type</b>	Incandescent LED
<b>Switch Load Capacity Watts</b>	1250W
<b>Switch Load Capacity Volt-Ampere</b>	10A
<b>Color</b>	White

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0xFF0C
<b>Z-Wave Product Type:</b>	0xFF00
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.71.01
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

(Continued)

Mini Smart Plug

Association Group Information

Group # / Max      Description

Nodes

1 / 5                  Z-Wave Plus Lifeline

2 / 5                  basic set command

Supported Command Classes (17):

Association Group Info	Association V2
Basic V2	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Multi-Channel Association V3
Notification V8	Powerlevel
Security S0	Security S2
Supervision	Switch Binary
Transport Service V2	Version V2
Z-Wave Plus Info V2	

Controlled Command Classes (1):

Basic V2