



Amazon Echo Quick Start Guide



PART 1: PREPARATION

- Amazon Alexa Account(users required to register their own account).
- Smart Life APP.
- Echo, Echo Dot.IFTTT and other Amazon voice-controlled devices.
- Our samrt devices(For instance smart plug).


Note: After the configuration is successful, rename the decive name, it is recommended to use English letters as they are more convenient to be pronounced.

 Login with your Alexa account and password (if you do not have an account, please register firstly). After login, press the menu at the top left corner, then press "Settings", and select "Set up a new

PART 2: SET YOUR ECHO SPEAKER VIA ALEXA APP

- Select a device f.i.Echo. When the page on the right side appears, long press the small dot on Echo until the light turns to yellow. Then click "Continue" option on APP. (Note: Do not open the VPN software on the phone during this time).
- Selct the user's Wi-Fi network and wait a few minutes.
- After a brief voice introduction, click next step. Then it will skip to the Home Page automatically. And at this time. Echo has connected to the Wi-Fi through Alexa App successfully.

PART 3: ENABLE SKILLS ON ALEXA APP



 Select skills from the option colum then search for "Smart Life" in the input box, select "Smart Life " from the search results, then click "Enable (Note: If you have already bound an account, you can click **Disable Skills** to remove the binding, then click

Enable Skills to continue to bind the

Enter Wi-Fi password

Picture2

PART 3: ENABLE SKILLS ON ALEXA APP

 Input the user name and password that you have registered previously.
(It only supports accounts in the United States). When you see the page on the right, it means that Alexa connected to the Smart Life

Done # skills-store.amazon.cc × amazon alexa Smart Life has been successfully

PART 4: CONTROL DEVICES VIA ALEXA APP


- After the previous operations are successful, the device can be
- After the previous operations are successful, the device can be controlled Via Echo.
 Discover Devices: Firstly, users required to say Echo: "Alexa, find my device", Echo will start to discover the device which has been added into the "Smart Life" APP previously, and it will take 20 seconds to display the results.
 Or you can click "Descover Devices" in Alexa APP, and it will show in the list the devices that have been discovered.
- Note: "Echo" is one of the names used for wake-up the App, and you can also use another two names i.e. Alexa / Amazon.

PART 5: LIST SUPPORTING SKILLS OF ECHO ou can control your device with the following commands:


- Alexa, turn on/off bedroom light.
- Alexa, set bedroom light to 50 percent.
 Alexa,bright / increase bedroom light.
- Alexa,dim / decrease bedroom light.

Note: The name of the device must match with the name in **Smart Life** APP.

PART 5: PRODUCT WIRING DIAGRAM



PART 5: PRODUCT WIRING DIAGRAM



Square Base WiFi Switch Wiring (Nuetral and Live Wires

PART 5: PRODUCT WIRING DIAGRAM





Wi-Fi Smart PRODUCT GENERAL INSTRUCTION MANUAL

PART 1:DOWNLOAD, REGISTRATION & TEST

- Scan the QR code to download "Smart Life" APP or you can search and download the app directly from APP Store / Google Play.





PART 2:ADD DEVICE & PAIRING INSTRUCTION

- 1.Add device (Rapidly blink mode)
- Press the button for about 7seconds until the WiFi red indicator flash rapidly showing the WiFi module is on paring status.
- Press the icon "+"at the right corner of the interface to add your advice.
- Choose "All device", then choose "Switch".
- Press "Confirm indicator rapidly blink"(picture1).
- Input your Wi-Fi password ,then press "Confirm"(picture2).
- Wait until the device is added successfully, then click "Completed" ● Note: 1.Users could rename the device by pressing the icon" ☑ "at the riaht corner.
- Note: 2. The device will be on paring mode (rapidly blink) if power on/off three times continuously (in 1-2 seconds between each power off).







PART 2:ADD DEVICE & PAIRING INSTRUCTION

- 2.Add device (AP mode,slowly blink)

 Press the button for about 7seconds until the WiFi red indicator flash rapidly, release the button and press it again for about 7 seconds until the WiFi indicator flash slowly.
- Press the icon "+"at the right corner of the interface to add your advice.
- Choose "All device", then choose "Switch" Choose "AP mode" at the right corner of the interface to add your advice.
- Press "Confirm indicator slowly blink".
- Input your Wi-Fi password ,then press "Confirm".
- Connect the phone's Wi-Fi to the device's hotspot "Smartlife-XXXX"
- (by choosing at left corner)(picture3). Return back to pairing interface.
- Wait until the device is added successfully, then click "Completed".
- Note: 1.Users could rename the device by pressing the icon" ∠ "at the right



PART 3:WIFI CURTAIN SWITCH PARING INSTRUCTION

1. WiFi Paring:

• Press the left open or right close button(not the middle stop button) for about 7 seconds until the red indicator flash, then follow the above part 2 steps to finish WiFi paring.

2. Curtain Track Time Setting :

• When the curtain is completely in open status, press the middle stop button for about 7 seconds until the blue indicator flash and release your finger. The curtain will start closing automatically. Touch the middle stop button again immediately when the curtain is closed completely(should be in same time). The blue indicator will stop flashing, and finish the curtain track time setting.

PART 4: RF433 REMOTE PAIRING INSTRUCTIONS

RF Code Clearance Instruction:
When the product is turned off, press on/off button (or touch the desired gang centre circle on touch switch) about 3 seconds, and then the blue indicator will flash, then release on/off button (or the desired gang centre circle on touch switch). Continue to press on/off button(or touch the desired gang centre circle on touch switch) until the indicator stops flashing, which means the clearance code is completed successfully.

(Note: If the product has RF and Wi-Fi functions, the red indicator light wil

flash firstly during this process;if the product does not has RF function,the red indicator light will not flash during this process.)

 RF Paring Instruction:

When the product is turned off, press on/off button (or touch the desired gang centre circle on touch switch) about 3 seconds, then the blue indicato will flash, which shows that the RF is in a paring condition, and then press the pairing key on the remote controller accordingly. Paring is completed successfully. Please pay attention to check if there is any damage caused during the teansportation. Once found defective / damaged, please contact the supplier for a replacement. Please follow the specification instructions strictly and keep the product used in a good and safe condition.

PART 5: ATTENTIONS

- Please install the switch in a proper position and keep it out of reach of children.
- When using socket-type products, please keep the plug fully inserted into the socket.
- The total power of the socket products while connected to the socket shall not be greater than the maximun power of the socket.
- Input and output for switch-type products shall not be connected incorrectly.
- The total output power of switch-type products shall bot be greater than the maximum power of the socket.
- Do not dissemble the product; otherwise it may cause security risks.

