

## Series 4, Induction cooktop, 60 cm, Black, PUJ611BB5E







HEZ9SE060 6 pieces Set



HEZ32WA00 Wireless food thermometer
HEZ390090 Wok Set consisting of 3 Items
HEZ9ES100 Espresso maker 4 cups
HEZ9FE280 Iron pan Ø 18 / 28 cm
HEZ9SE030 Set of 2 pots and 1 pan
HEZ9SE040 4 pieces Set

# The induction cooktop: cook fast, clean and safely while using very little energy.

- **TouchSelect**: Selection of the desired cooking zone and easy setting of the desired power level.
- 28 cm cooking zone: for small and large pots and pans.
- Power Boost: up to 35% faster heating compared to highest power level
- Quick Start: start straight away and select the desired cooking
- **Restart**: restores cooktop settings in case of an unintentional cooktop switch-off.

Product name/family:			
Energy input:			
Total number of positions that can be used at the same time: 3			
Min. required niche size for installation (HxWxD):51 x 560-560 x			
490-500 mm			
Width of the appliance:592 mm			
Dimensions (HxWxD):			
Dimensions of the packed product (HxWxD): 126 x 753 x 603 mm			
Net weight:9.3 kg			
Gross weight:			
Residual heat indicator:separate			
Location of control panel:Front			
Basic surface material:Ceramic glass			
Color of surface:Black			
Length electrical supply cord:			
EAN code:			
Voltage:			
Frequency:			







### Series 4, Induction cooktop, 60 cm, Black, PUJ611BB5E

## The induction cooktop: cook fast, clean and safely while using very little energy.

- 60 cm Cooktop Induction: space for 3 pots or pans.

#### Flexibility of cooking zones

- Cooking zone rear left: 280 mm, 2.6 KW (max. power 3.7 KW)
- Cooking zone rear right: 145 mm , 1.4 KW (max power 2.2 KW)
- Cooking zone front right: 210 mm, 2.2 KW (max. power 3.7 KW)

#### Usage convenience

- Electronic TouchSelect +/- controls: control the power with imprinted +/- touch buttons.
- 17 power levels for each cooking zone: precisely adapt the heat with 17 power levels (9 main levels and 8 intermediate levels).
- Switch-off timer: switches off the cooking zone at the end of the time set (e.g. for boiled eggs).
- Count-down timer: an alarm sounds at the end of the time set (e.g. for pasta).

#### Time saving & efficiency

- PowerBoost function reduce the time to heat up large quantities of water: boil water faster with up to 50% more energy than at the highest standard level.
- QuickStart Quick and automatic first pot detection: when switching on, the cooktop automatically selects the cooking zone with cookware on it.
- ReStart Quickly reinstates previous settings: in case of unintentional switch-off, restore all previous settings by switching on the cooktop again within 4 seconds.
- Quick Stop: quickly switch off a cooking zone with one longer touch.

#### Design

- Frameless

#### Safety


- Digital 2-stage residual heat indicator: indicates which cooking zones are still hot or warm.
- Childproof lock: prevent unintended activation of the cooktop.
- Main switch: switch off all cooking zones at the touch of a button.
- Automatic safety switch-off: for safety reasons, heating stops after a preset time without interaction.

#### Installation

- Dimensions of the product (HxWxD mm): 51 x 592 x 522
- Required niche size for installation (HxWxD mm) : 51 x 560 x (490 500)
- Min. worktop thickness: 16 mm
- Connected load: 4.6 KW
- Power cord: 1.1 m, connected directly



## Series 4, Induction cooktop, 60 cm, Black, PUJ611BB5E



- A Minimum distance from the hob-current to distance depth.


  8 Monocast depth.


  Citra destance between the surface of the eyest due and the fact of the food of the eyest as well as \$0 mm. See special requirements to the eyest.
- The working improving the high is, installed installed installed installed in accross 60 kg; suitable substitutes must be used if required.

D	E	F
585-600	93	2.35
> 000	26.5%	> 50

① Ventilation gap must be present

All measurements in mm





Measurements in mm.