

Buttons and Ports

h Power/TWS/Mode

Short press to switch mode. Double click to TWS .conntect or disconnet with two speakers. Long press and hold to turn the speaker on/off

- Volume Down/Previous Button Short Press to turn down the volume Long Press to go to previous song (previous channel in FM).
- + Volume Up/Next Button Short Press to turn up the volume Long Press to go to next song (next channel in FM).
- Mode/Pause/Plav Short press to pause/play the music. Short press to accept an incoming call. Long press to reject an incoming call.

Long press 2s disconnet with BT.


Double click to call back.

Charging Your Device

Plug the included USB type-C cable into the speaker's charging port, and connect the other end of the cable to a power adapter (not included). Allow approximately 2.5 hours to full charge the

When the battery is low and the red light blinks, please charge it. The indicate light is red color when it's charging. The red light will be off when it's full charged.


Note: We recommend using a USB wall adapter with a DC 5V=1A



Specifications

- -Model Name: BT-7X0
- -Portable Wireless Speaker
- -Output Power: 4.5W
- -Input Power: 5V == 1A
- -Impedance:4Ω
- -Signal to Noise Ratio:≥ 78dB
- -IPX7 water-resistant.sprayproof
- -Built-in rechargeable battery
- -Built-in Mic
- -Range 33ft(10m)
- -Frequency Response: 180Hz-12KHz
- -TWS Svnc Mode(True Wireless Stereo)
- -Up to 10 hours of playtime (battery life ismeasured as number of playtime with volume set at50%)

Initial Setup



- 1. Once your speaker is fully charged, press and hold the "也" Power button until you hear a voice prompt indicating the device has entered BT paring mode.
- 2. On your smartphone or tablet, search for the BT device named "QFX BT-ZX0" and tap to connect.
- 3. A prompt will play once pairing is successful.

- 1. When you turn on the speaker but no connection, it will automatically shut down after 10 minutes.
- 2. When you connected the speaker but no playback, it will automatically shut down after 20 minutes.

TWS Sync Mode



This device features TWS (True Wireless Stereo) technology, which allows to play music on two of these speakers simultaneously, creating a surround sound experience.

- 1.Long press the "**b**" about 2s on both speakers to turn them on, and the blue light flashes.
- 2.Quickly double-click the "(1)" on any one speaker, a prompt sound "connected"indicates the speakers enter into pairing mode, the indicator light of one speaker turned blue.
- 3.On your smartphone or tablet, search for the BT device named "QFX BT-ZX0" and connect it, you could hear the sound "connected" again, which means connect successfully. You can enjoy the music with two speakers together.

Notes:

*In TWS Mode, turn off one of the speakers, both of them are off. *Double-click the "**b**" button will be TWS disconnected.

FM Radio Mode

- . Short press the " O " button to switch to the FM broadcast mode, indicator light blue.
- 2. Short press the "▶" button to automatically scan for radiostations. Short press again the ">" to remain on a selected channel.
- 3. When the scan is complete, the station is automatically stored, long press the "+" to select the next station,long press the "-" to select the previous station.

Insert the included USB type-C cable into the charging port while in FM mode to use it as an external antenna and improve signal.

Hands-Free Calling

- Volume Down Short Press once to decrease volume
- + Volume Up Short Press once to increase volume
- Mode/Answer Button Short press to accept an incoming call. Long press to reject an incoming call. Long press 2s disconnet with BT. Double click to call back.

Resetting Your Device

If your speaker is not operating properly, you may need to reset it. To do so, long press the " b " power button for approximately 8s until the speaker powers off, and then power it on again as usual.





LIMITED PRODUCT WARRANTY POLICY

Refore returning your Product for service under this Warranty please (i) read the instruction manual carefully and visit our website at www.ofu.cs.com for Produ updates and extended support documentation (e.g., Common Troubleshooting Guides); (ii) if you are still having trouble with your Product, please contact the QFX Customer Support Department

Subject to the terms and conditions herein, QFX, Inc. (herein after called "QFX") warrants to the original purchaser of the Product
("Customer") that for the applicable Warranty Period listed below, the Product will be free from defects in material or workmanship under normal, non-commercial use

ourchase. If Customer returns a defective Product (or any component thereof) during the applicable Warranty Period, QFX will, at its option, during the specified Coverage Periods for Parts and Labor (as applicable either: (i) repair the Product (or, as applicable, any component thereof) or (ii) replace the Product (or, as applicable any component thereoft with a new or refurbished Product (or, as applicable, any component thereoft, in either case free of charge to Customer for Parts and/or Labo recoing states the Customer's exclusive remedy and QFX sole liability for breach of the limited warranty contained herein.

toegong states the Lucitomer is occurred entirely allow Life to execute or executive contracts of the entirely accurate the contract of the entirely accurate the

DICENT IN EXPRESS INVESTIGATION TO THE MANIMUM ENTER HEADING THE POPULATION TO THE POPULATION OF THE P

THE CAMILLATIVE PRODUCT HESPEND BY THAT CUSTOMERT OR THE PRODUCTS CALISING THE DAVAGES, If ANY.

THIS Warranty light exclationer specificity, and Customer may also have other rights that very from jurisdiction to jurisdiction to jurisdiction. Warring Some Products may contain components that are small enough to be existed evaluated. Please keep out of reach of children, in order for the extra to be processed, you must send the Product products of the product of the p



2957 E. 46th Street | Vernon, CA 90058

(800) 864-CLUB (2582) or (323) 864-6900 qfxusa.com
 Hours of Operation: Monday - Friday, 9am - 5pm PST

vish to return by category or model number prefix, QFX will not provide any return or refund to any customer for merchandise and will only honor the Limited Warranty restriction

Please make sure to follow all directions prior to shipping back your item. If you are not sure what the shipping cost for your item is, or if your item category conflicts in the table below

Earphones, Headphones, Pocket Radios, & Small Bluetooth vSpeakers	\$5.00	1 Year	1 Year
Personal Stereos	\$10.00	1 Year	1 Year
Portable Radio/Cassette	\$15.00	1 Year	1 Year
Large Portable Radio Cassette	\$20.00	1 Year	1 Year
Mobile Audio	\$10.00	1 Year	1 Year
Pro Audio SBX Systems	\$75.00	1 Year	1 Year
Pro Audio PBX Systems	\$75.00	1 Year	1 Year
Televisions	\$25.00	1 Year	1 Year
Telephones	\$10.00	1 Year	1 Year

damages, so the above limitations and exclusions may not apply to you. This warranty gives you special legal rights and you may have other rights which vary from jurisdiction







