

AK84 : USB Wired Model

AK84S: USB+Bluetooth Dual Model

## Better for MAC

SKYLOONG



Bluetooth condition: (1) If one of blue led is flashing, the keyboard is connecting the BT equipment.

In step: In-space ON/OFF the BT mode, link to USB mode.

★ Symbol in PBT Keycap is for reference, please subject to the real keyboard, press Fn with function keys.




AK84 : USB Wired Model

AK84S: USB+Bluetooth Dual Model

## FN+6 Also for WIN

SKYLOONG



FN tip: Unlock/Lock the WIN key, prevent windows start pop-ups in the game.



FN tip: If your keyboard is modified VIDPID by the driver, The driver does not recognize your keyboard, long press FN+F6 for 3 seconds, restore default VIDPID, restore driver recognition.

★ ABS double-shot keycaps

FN tip: If you are not sure which mode the keyboard is in now, press FN key and observe what LED is on to confirm.

Downloaded from thesmanual.org

# fn function description (Double-click FN to light FN's white LED, FN function is held, click FN again to escape from holding status).

## Define mode

Key	Function
Standard mode	Standard mode, all buttons can not be user-defined. User can customize your own personally keyboard by the following 4 modes. (Standard mode F12 is strongly recommended (note: in the custom mode, except FN key, other keys can be modified, key values some of the FN + " " function can be also modified except the backlight, Bluetooth and system control. The FN button can not be moved, but user can define your own FN1/FN2/FN3 at any key on the keyboard in the custom mode).
FN + 0% Driver mode	① FN + 0%, in the driver mode layer, " 0% " lights white LED, system special function (For example: You may design a piece of more than 32 bytes in a key in the driver mode while it's unavailable in those onboard mode layer) and backlight can be set in this mode. You must keep the driver running and the keyboard connected with the driver. Press FN + 0% again, back to standard mode.
FN + 0% Onboard mode Layer1 / FN1 Win mode	① FN + 0%, onboard mode layer 1, " 0% " lights white LED, no need to run and connect the driver. The keyboard works in the custom key functions and user can modify the key functions and mouse settings by the driver and these settings can be downloaded and saved to the keyboard. The reference saving Win mode setting is realize the fastest operation of win users.
FN + 75% Onboard mode Layer2 / FN2 Mac OS mode	① FN + 75%, onboard mode layer 2, " 75% " lights white LED, the reference setting keyboard of MAC OS, Mac "control, option, command" key will be in the original position, user can modify the settings by the driver, download and save to the keyboard, no need to run and connect the driver when use the Mac's function settings. Press FN + 75% again, back to the standard mode.
FN + 8% Onboard mode Layer3 / FN3	① FN + 8%, onboard mode layer 3, " 8% " lights white LED, The reference setting: Some special function keys, or combination keys, or macro keys, these settings of this mode can be called by the key FN3 in Layer1(Layer1). All settings in this mode can be modified and saved to the keyboard. Press FN+8% again, back to the standard mode.

## Backlight settings (Can not modify)

Key	Function
FN + 0	① Light effect power on
FN + 0	② Backlight ON/OFF
FN + -	③ Backlight mode 1 ~ 5 (Can modify)
FN + +	④ Backlight mode 0 ~ 0
FN + +	⑤ Backlight brightness -
FN + +	⑥ Backlight brightness +
FN + +	⑦ Backlight Effect Speed -
FN + +	⑧ Backlight Effect Speed +

## Bluetooth settings (Only for Bluetooth mode can not modify)

Key	Function
FN + 0/0/0	① Bluetooth ON/OFF switch Link to USB mode or the Bluetooth equipment.
FN + 1/1	② Long press: The red/green LED of 1/1 keycap will flash. The #1 Bluetooth equipment can be paired. Press: The keyboard will connect the #1 BT equipment or disconnect.
FN + 2/2	③ Long press: The red/green LED of 2/2 keycap will flash. The #2 Bluetooth equipment can be paired. Press: The keyboard will connect the #2 BT equipment or disconnect.
FN + 3/3	④ Long press: The red/green LED of 3/3 keycap will flash. The #3 Bluetooth equipment can be paired. Press: The keyboard will connect the #3 BT equipment or disconnect.

note: If the Bluetooth pairing failed or not paired, please to pair. If the Bluetooth pairing is successful at the equipment, but the keyboard can not work still, please delete this keyboard in the Bluetooth list, turn off Bluetooth of your PC or Mobile, restart the keyboard, and to pair.

## System Control (Can not modify)

FN + -	① Mechanical dual model series long press for 3 seconds to on/off the keyboard.
②	Long press the ② label at the bottom of the Optical dual model keyboard for 3 seconds to turn on/off brightness, when users don't have this function.
FN + 4/4	③ Turn off/on the charging indicator low voltage alarm, the wheel version does not have this function.
FN + control	④ Display/Close the time setting, when LED on 2 minutes sleep, 10 minutes sleep, 30 minutes sleep, 1 hour sleep.

## FN function (Reference Settings, can be modified by driver)

Key	Mac mode function	Win mode function
F1	① Screen brightness - for Mac	F1
F2	② Screen brightness + for Mac	F2
F3	③ F1, F2 for Mac	F3
F4	④ F1, F2 for Mac	F4
F5	⑤ Backlight brightness - for Mac	F5
F6	⑥ Backlight brightness + for Mac	F6
F7	⑦ Previous	F7
F8	⑧ Play/Pause	F8
F9	⑨ Next	F9
F10	⑩ Mute	F10
F11	⑪ Volume -	F11
F12	⑫ Volume +	F12
F13 (P/B)	⑬ One click call Sin for Mac	PS
F14 (SL)	⑭ One click call handwriting for Mac	SL
F15 (P/B)	⑮ Enter/Enter for Mac	PB
FN + 0/0/0	home	home
FN + 0/0/0	end	end
FN + Win	⑯ Lock/Unlock Win key	⑰ Lock/Unlock Win key



From The community, For The community!  
CE FCC E RoHS

