

Manual---Shenoy SH007

Shenoy

TECH SPECS:

Bluetooth Version: 5.1

Bluetooth Range: 10 meters

Driver Unit: $\phi 40\text{mm}$

Impedance: 32Ω

Sensitivity: $100 \pm 3\text{dB}$

Frequency Response: $20\text{Hz} - 20\text{KHz}$

Cancellation Level: $22\text{dB} \pm 3\text{dB}$

Battery Capacity: $3.7\text{V}/750\text{mAh}$

ANC Working Time: Up to 22 hours

Bluetooth Working Time: Up to 30 hours

Standby Time: Up to 300 hours

Charging Time: Approx 3 hours

Charging Port: Micro-USB

FUNCTION PICTURE



Description of all parts :

1. LED Indicator
2. Microphone
3. 3.5 mm UAX Port
4. Micro-USB Charging Port
5. ANC button: on or off
6. Volume down or Previous song
7. Power on/off or Pause/Play or Calling/Answer
8. Volume up or Next song

Pairing Steps:

1. Press **▶||** for 5 seconds to put into pairing mode (the indicator light will alternate between red and blue).
2. Go to your Bluetooth settings on your device and find the Bluetooth pairing name "Shenoy SH007". Pair your device, then it will be connected, when connected successfully, only blue light flash.

Product Usage:

1. Power on : Press and hold the **▶||** for about 3 seconds, until blue light flashes.
2. Power off : Press and hold **▶||** for about 3 seconds, the indicator light will turn off.
3. Answer a call : when a call is coming in, Answer the call by pressing **▶||** once.
4. Reject a call : Press and hold **▶||** for about 2 seconds.
5. Redialing the last number : Double click **▶||** button.
6. Volume "+" and next song : Press **▶▶+** quickly for next song, press and hold for volume up.
7. Volume "-" and previous song : Press **◀◀** quickly for previous song, press and hold for volume down.
8. Play / Pause music : when you listen to the music, you can play or pause the song by pressing **▶||** button.
9. ANC mode: Push **ON OFF** button to open / close the function.
10. Reconnected : when reopen the bluetooth mode, the headphone will reconnect to the nearest devices.
11. When insert the line in or USB cable, the headphone will power off rapidly, then switch to wired mode, and all bluetooth buttons are not workable.
12. Charging port with USB charging cable.

Voiced in Singapore
Made in China