GPEESTRAC® Enjoy Hands-free Communication with HSP-B3 Headset

warning:

voltage higher than 5%

headset and it will stop working

HSP-B3

USER MANUAL

DO NOT use any power adapter with output

Input voltage higher than 5V may damage the

CEFC CONT

Rotatable180" ---- + BUTTON ex Sections has - Annual treatment Call

HEADSET OVERVIEW



lead the Math function to star and Mate hatte

for 5 seconds at the same time.

2. Bestperformancewith fullbattery Noise Cancelling Double Microphone Noise Cancelling for Wind Noise Reduction Microphone Mute Button During a call tap the Mute butten to mute the micro-

1.5~2uh(Full chargeme): 5 uV 120mA

phone Youwill hear "mute on prompt Tap the Mute button again toopen the microphone and hear "mute off" confirmation "use Siri/Google On the standby Status Tap the Mute button to enable (Siri/Google) voice Assistant Function

voice command LED Light

Charge

after voice prompt "BIP" then you can say your voice command. One click can only process one , Under charging: Red indicator is on;

After charging full: The blue indicator on;

Low battery: Red indicator flashes twice

How to Reconnect

with voice prompt

nal Bluetooth USB Adapter

turn)to enable pairing state; . Select HSP-B3 2 Recover the Wireless headset's default settings 4. Input password:0000 if needed(default password NOTE: If your PC/Notebook does support Bluetooth function or remind you need driver you may need to use an

How to Connect to Bluetooth devices

and red light And you will hear the voice prompt

2 Activate Bluetooth and set it to search for new

Android**-Rhietooth- On > Scan for devices

*PC/Notebook: Bluetooth Setting: On >

I you headset will try to reconnect the

*iPhone: Settings > Bluetooth > Off

the pairing status

Bluetooth device

connection:

devices

Power on & pairing status : press and hold the mult

function button until the indicator light flasnes blue

"rower on" Then the neadset will antomatically enter

After restart the mobile phone remove all pairing data in the Wireless of the mobile phone: Cautions After the Wireless headset has entered in the pairing mode it will connect within 2min otherwise, the headset will automatically turn off after 5 minutes: Hold the ME button and Mute button for 5

seconds at the same time

The headset program is error:

, If the neadset doesn't try to reconnet, Please click

the multi-function button once or manully con nect with

the wireless equipment men u of the mobile phone;

The mobile phone can't find the headset

1, "the headset is not under ON andstandbystate;

After turning off the headset Hold the Multi

-funtion button(red and blue indicator flashes by

I he program of the mobile phone is error;

Troubleshooting

Possible reasons

Solutions:

1. The volume of the mobile phone is unsmtable; Charge headset for about 30min and then the red indi-2 The Wireless headset and mobile phone are not cator may lighton; Cautions: connected correctly: The Wireless headset is out of the working range: It will drop the capacity and service lite of the battery if it is over charged or the Wireless headset is store d in

No sound Or intermittently from the

headset

Possible Reasons:

Solutions: Agiust the volume in the mobile phone. 2 Operate with the reference of the use steps;

the environ ment such as closed car-TECHNICAL SPECIFICATIONS Keep the heagset in the range of 10m to the mobile phone without anyobstacle: Cautions Do not have any other operation when searching headset for avoiding program error;

Please use headset near the mobile phone to assure

This headset volume actiustment can be synchronia

best effect. (Keep no opstacles or walls between the

zed with the iphone when used with other mobile

phones you need to acjust the volume of the mobile

headset and the connected device) .

phone and headset at the same time.

"vyarning 1. The product is equipped with lithium pattery Please do not expose the product to intense sun light burn or throw it into the fire to avoid explosion 2 This product can not be charged with a charger whith output voltage is higher than 5v otherwise it will burn out the headset by over-voltage Frequently Asked Questions

wureless devices are susceptible to interference that

may attect audio quality and result in static. To avoid

blocking the Bluetooth signal follow these guidelines:

Why do I hear static noise on my headse to

III Charging red indicator doesn't light on

The headset has not been used for a long period;

Possible Reasons

(include walls, doors andwindows) 3 Avoid environ ments where computers/microwave ovens/high concentrations of WiFi are present 4 Keep your nearset and mobile phone on the same side of your body 5 Avoid placing your mobile phone in a back pocket Note: Low battery capacity in your headset and mobile phone may affect the Bluetooth range FCC Requirement changes or medifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment

This device complies with Part 15 of the FCC Rules

Operations subject to the following two conditions

(2) this device must accept any interference received

(1) this device may not cause harmful interierence and

including interference that may cause undesired opera-

Daireddevice does notexceed 10 m

radio signals between paireu de vices

. Make sure the distance petween your headset and the

2 Make sure there is a direct line of sight betweenyour

headset and phone Avoid placing objects that can block