Disclaimer. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



APC Smart-UPS Battery Pack 48V, 3360VAh

UXABP48

Overview

Lead time Usually in Stock

Main

Main Input Voltage	48 V DC	
Product or Component Type	Battery	
Main Output Voltage	48 V DC	
Battery Type	Lead-Acid battery	
Provided Equipment	Installation guide User Manual	
Range of Product	Smart-UPS Battery Systems	

Batteries & Runtime

Device mounting	Enclosed battery cabinet	
Included Battery Modules	0	
Battery Slots Empty	0	
RBC Quantity	1	
Battery Voltage	48V	
Replacement battery	APCRBC119 ☐	

Physical

_		
Color	Black	
Height	12.20 in (31 cm)	
Width	17.60 in (44.7 cm)	
Depth	29.69 in (75.4 cm)	
Net Weight	280.58 lb(US) (127.27 kg)	
Mounting Mode	Not rack-mountable	
USB compatible	No	

Environmental

Ambient Air Temperature for Operation	32104 °F (040 °C)	
Relative Humidity	095 %	
Operating altitude	010000 ft	

Ambient Air Temperature for Storage	5113 °F (-1545 °C)
Storage Relative Humidity	095 %
Storage altitude	050000 ft (015240 m)

Ordering and shipping details

GTIN 731304257356

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	17.01 in (43.2 cm)
Package 1 Width	32.99 in (83.8 cm)
Package 1 Length	20.00 in (50.8 cm)
Package weight(Lbs)	314.67 lb(US) (142.73 kg)

Contractual warranty

Warranty 2 years repair or replace



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

☑ Environmental footprint	
Carbon footprint (kg CO2 eq, Total Life cycle)	654
Environmental Disclosure	Product Environmental Profile

Use Better

Packaging made with recycled cardboard	Yes
Packaging without single use plastic	No
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
REACh Regulation	REACh Declaration

Use Again

○ Repack and remanufacture	
Circularity Profile	End of Life Information
Removable battery	User replaceable
Take-back	Yes