



PARTYBOX ENCORE 2

Portable party speaker with 1 mic



Bring the star power to your next party.

Power up the JBL PartyBox Encore 2 and let the good times roll. With this portable speaker, you'll want to play DJ at every event, with smooth JBL Pro Sound, a light show to fit the mood, and a mic for your emceeing pleasure. Feel that extra oomph in your chest from the epic highs and deep lows, whether you're playing a new pop ballad or going with a classic slow jam. Once you've nailed the soundcheck, it's time to turn up the ambiance with a light show that grooves to your beats.

Ready to run the show? Grab the digital wireless mic and become your own emcee or karaoke host! You can also customize your sound with adjustable echo, bass, and treble controls to make sure you sound just right. From open rooftops to crowded basements, the JBL PartyBox Encore 2 knows how to adapt, with its grab-and-go handle and IPX4 splash-proof design.

What's better than one JBL PartyBox Encore 2? Two! Pair them up for true stereo vibes or link with other JBL Auracast™-enabled speakers for an even wilder dance party. And if 15 hours of nonstop jams isn't enough, grab a spare rechargeable battery to keep the music going. Make the vibes immaculate with the JBL PartyBox app, where you can control your playlist, add fun sound effects, and pick the perfect light show mood—all while you're doing the worm on the dance floor.

Whatever the occasion, the JBL PartyBox Encore 2 knows how to bring all the feels.

Features

- ▶ JBL Pro Sound gets an AI Sound Boost
- ▶ Dynamic lightshow
- ▶ Up to 15 Hours of play time
- ▶ Multi-speaker connection by Auracast™
- ▶ Karaoke anywhere—or play live
- ▶ Control your party, right from the JBL PartyBox App
- ▶ IPX4 Splash proof
- ▶ Flexible handle and ergonomic design
- ▶ Recycled plastic, plus FSC certified paper packaging





PARTYBOX ENCORE 2

Portable party speaker with 1 mic



Features and Benefits

JBL Pro Sound gets an AI Sound Boost

Pop ballads, slow jams and everything in between, we've got the sound to make your playlist shine. Feel that extra oomph in your chest as the silk dome tweeters and powerful woofers bring those epic highs and deep lows. Want to turn it up even louder? Your music will still sound crystal clear as the AI Sound Boost delivers more powerful sound with less distortion.

Dynamic lightshow

Is it really a party without a lightshow? Dance the night away with glowing light patterns and strobe effects that would make any club jealous.

Up to 15 Hours of play time

Keep the good vibes going on a single charge with up to 15 hours playtime. And if 15 hours of nonstop jams isn't enough, pop in a spare rechargeable battery to keep the music going. Or charge for 10 minutes and get an extra 80 minutes of play time.

*Spare replaceable battery sold separately

Multi-speaker connection by Auracast™

Bigger parties call for even bigger sound. Pair two PartyBox Encore 2 for true stereo vibes via Auracast™, or connect multiple JBL Auracast™-enabled speakers wirelessly and let your music grow with your party size.

Karaoke anywhere—or play live

Grab the digital wireless mic and become your own emcee. With adjustable echo, bass, and treble controls, you'll always sound smooth. Or dance to your favorite playlists with aux-in and USB-C connectors. Looking to put on a live set? The guitar input comes with pre-gain and a volume knob so you can crank it up and perform.

Control your party, right from the JBL PartyBox App

Don't feel stuck on speaker babysitting duty. Control your music, EQ settings, and lightshow from the JBL PartyBox app, wherever the party takes you.

IPX4 Splash proof

Spills and splashes happen...don't sweat the mess. The JBL PartyBox Encore 2 is IPX4 splash proof so your flow is never interrupted.

Flexible handle and ergonomic design

Take your sound down the block or go global--whichever you choose the JBL PartyBox Encore 2 is ready to go with its flexible handle and ergonomic design.

Recycled plastic, plus FSC certified paper packaging

The JBL PartyBox Encore 2 incorporates post-consumer recycled plastic. It's also packaged in FSC-certified paper printed with soy ink.

Technical Specifications

- ▶ Transducers: 1 x 5.25 inch (135mm) woofers, 2 x 0.75 inch (20mm) Dome tweeters
 - ▶ Output power: 100W RMS (IEC60268)
 - ▶ Power input: 100 - 240V ~50/60 Hz
 - ▶ Frequency response: 40Hz - 20kHz (-6dB)
 - ▶ Signal-to-noise ratio: > 80dB
 - ▶ Battery Type: JBL Battery 200, Li-ion battery (7.4V/4722mAh)
 - ▶ Battery charge time: < 3.5 hours (Speaker off mode)
 - ▶ Music play time: up to 15 hours (varies by volume level and audio content)
 - ▶ Cable type: AC power cable (type varies by regions)
 - ▶ Cable length: 2.0m / 6.6 ft
 - ▶ USB charge out: 11V / 2A (Max) (Speaker off mode)
 - ▶ USB format: FAT16, FAT32
 - ▶ Bluetooth® version: 5.4
 - ▶ Bluetooth® profile: A2DP V1.4, AVRCP V1.6(SW), TMAP1.0, PBP1.0
 - ▶ Bluetooth® transmitter frequency range: 2.402GHZ~2.4835GHZ
 - ▶ Bluetooth® transmitter power: ≤ 16 dBm (EIRP)
 - ▶ Bluetooth® transmitter modulation: GFSK, π/4 DQPSK, 8DPSK
 - ▶ USB Supported formats (Not for EMEA region): .MP3, .WAV, .FLAC
 - ▶ Aux-In: 370 mV RMS (3.5mm connector)
 - ▶ Mic-In: 20 mV RMS
 - ▶ Guitar-In: 100 mV RMS
 - ▶ Bluetooth/USB input: -9dBFS
 - ▶ Product dimensions (W x H x D): 319.5 mm x 338.6 mm x 263 mm (12.58" x 13.33" x 10.35")
 - ▶ Net weight: 6.4 kg / 14.11 lbs
 - ▶ Packaging dimensions (W x H x D): 385 mm x 365 mm x 350 mm / 15.16" x 14.37" x 13.78"
 - ▶ Gross weight: 9.15 kg / 20.61 lbs
- ### Wireless Mic Specification
- ▶ Carrier frequency: 2404~2478MHz
 - ▶ Working Range: ≤30M (100')
 - ▶ Frequency Response: 50Hz~15KHz
 - ▶ Signal-to-Noise: >59dBA
 - ▶ Transmitting Power: <8.5dBm (EIRP)

What's in the Box

- 1 x JBL PartyBox Encore 2 speaker
- 1 x wireless microphone
- 1 x mic holder
- 1 x Quick-start guide
- 1 x Safety Instruction and Warranty Card
- AC power cord - quantity and plug type vary by regions.

