



Z-Wave Protocol Implementation Conformance Statement

FIBARO Wall Plug E/F

General Information

Product Identifier: FGWPE/F-102
Brand Name: FIBARO
Product Version: HW: 2 FW: 3.15:03.02
Z-Wave Certification #: ZC10-16035016

Z-Wave Product Information

Supports Z-Wave Beaming Technology? Yes
Supports Z-Wave Network Security? Yes
Supports Z-Wave AES-128 Security S0? No
Supports Security S2? No
SmartStart Compatible? No

Z-Wave Technical Information

Z-Wave Frequency: CEPT (Europe)
Z-Wave Product ID: 0x1001
Z-Wave Product Type: 0x0602
Z-Wave Hardware Platform: ZM5202
Z-Wave Development Kit Version: 6.51.06
Z-Wave Library Type: Enhanced 232 Slave
Z-Wave Device Type / Role Type: On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max	Description
Nodes	
1 / 1	"Lifeline" reports the device status and allows for assigning single device only (main controller by default).
2 / 10	"On/Off (button)" devices in this group will be switched on or off when relay status is changed using the B-button (done via BASIC SET command frames).
3 / 10	"On/Off (power)" devices in this group will be switched on or off depending on the current load (done via BASIC SET command frames).

Controlled Command Classes (2):

Basic

Multi-Channel V4