



Models BF-16 and BF-22 User Manual for iPhone

Train - Contain - Bark Control



November 9, 2014

Introduction

Your patent pending, Bluefang electronic collar is the most advanced electronic pet collar you dog will every own. It provides you with powerful Bluetooth connectivity. It's training system is built on High Tech Pet's proprietary, proven, easy to use training techniques developed by some of the nation's most noted animal behaviorists and trainers. The model BF-16 is and advanced remote dog trainer that allows you to train your dog from a distance of up to 400 feet. The BF-16 also includes an advanced bark control feature bark control function uses that uses progressive sound and stimulus and has High Tech Pet's unique ability to distinguish between nuisance and intruder/ alarm barking. It can also prevent howling. The BF-22 gives you both these functions plus an electronic fence feature that works with any High Tech Pet brand electronic fence system to provide reliable, humane pet containment featuring our exclusive Pulsed Proportional Stimulus™ system.

The BF-22 contains serious hardware including the world's most powerful Bluetooth transceiver, an advanced microprocessor and a host of other built-in devices for current and future use. These include an electronic fence radio receiver for containment, microphone for bark sensing and accelerometer to measure your dog's activity level - just to name a few.

Perhaps, best of all your Bluefang collar has the unique ability to wirelessly accept new firmware giving you new and useful features as they become available.

Bluetooth Function



Logo lights up when it receives a command

The BF-22 receives commands and sends data to your iPhone via Bluetooth. Each time a command is received by the collar, it's illuminated logo lights up letting you know its working.

Adjusting the Collar Strap



The strap should be adjusted to a length that is snug but will allow you to comfortably put two fingers between the stimulus probes and your dog's neck. Adjusting the collar strap is simple but tricky in that the slider will not move without first sliding out the top strap layer. Slide the top strap layer out of the slider then adjust the strap to desired length using the male buckle end. Move the slider close to the male buckle and insert the top strap layer through the slider. This will prevent the slider from moving.

IMPORTANT NOTE: Your Bluefang collar is NOT designed to be a restraining collar. If you wish to use a restraining leash with your dog it must be attached to a separate collar. Do not attempt to use the Bluefang strap as a restraining collar. This may cause the probes to push too hard against your dog's skin and could cause injury to your dog.

Turning On Your Collar and Replacing the Battery



The collar battery also functions as an on/ off switch. Turn on your collar by clockwise rotating the battery pack on the underside of the unit. The battery pack acts as a 3 position switch. The positions are ON, OFF and REMOVE. To conserve battery life we recommend you turn the bat-

tery to the OFF position when not in use. Remove the battery by turning it fully counter-clockwise to its “Remove” position. To install a new battery align the arrow on the battery with “Remove” text. Then, turn clockwise to “Off” or “On” position. The logo will blink and the collar will beep when it successfully powers up.

Downloading the app



Download the iPhone app by scanning the QR code here or go to the app store and search for Bluefang Dog Trainer.

Scan to download iPhone app



Launch the app

Launch the app by clicking the app icon on your phone.



What's New Screen

The opening screen after the splash screen is the “What's New” screen. This is a live feed from our Bluefang server that will bring you the latest news, videos, training and pet care tips and allow you to get support ask questions and view the latest products

Main Menu takes you to collar functions



Live feed from web server brings you the latest news, videos, manuals, updates, products and fetatures. This start up screen will change often.

without having to download an app update. To view the What's New screen you must have an internet connection on your phone via WiFi or cellular data. If you are not connected to the internet or your connection is slow you can proceed directly to the Bluetooth app by pressing the Main Menu at the top left in the screen header.


Main Menu



The Main Menu lets you select from the current list of interactive collar functions. The BF-22 gives you remote training and Bark Control and Electronic Fence functions. To use these, you must first turn on your collar and link to it. With future firmware updates you may find useful, new collar features on the MAIN MENU.

Linking Your Collar

You may link to your collar by selecting any of the Main Menu Functions, “Train My Dog”, “Stop My Dog’s Barking” or “Contain My Dog”. From any of those feature screens press the SETTINGS link at the top right in the MENU BAR.



From any function screen
Press SETTINGS in the top
MENU BAR


Find Dogs Screen

The first settings screen is the FIND DOGS screen. It displays a list of all dogs your iPhone can detect. Your phone will detect a collar if it is turned on, in range and not already linked to another phone. Select the collar you wish to link and press CONNECT.



Naming Your Collar

You may use the EDIT NAME button to name your collar. You may name and set up an unlimited number of collars but, you may only link to one at a time. TRAINING and BARK CONTROL screens also allow you to customize stimulus settings which are discussed in the individual Training and Bark Control sections.



TRAINING SCREEN



Access the TRAINING screen by clicking TRAIN MY DOG on the MAIN MENU. The STATUS BOX at the top of the screen lets you know if the collar is linked and tells you when commands are sent by your phone and acknowledged by the collar. Initially this screen will display the message “No Dog Found” with a red background. Go to settings and link your collar as described above. When you return to the TRAINING screen it will take a second or two to re-scan for the collar and display “Ready” with a green background. Above the STATUS BOX the name of the linked collar is displayed.

The STATUS BOX displays both the link status and the command status. The link status is common to all screens that display the STATUS BOX.

Link Status

NO DOG
ENTER SETUP

No collar is has been linked. Got to FIND DOGS screen to search for collars to link.

SEEKING

Searching for a previously linked collar. This message may flash when switching screens.

READY

Collar is linked and ready to go.

LINK LOST

Link became broken. Collar lost power, went out of range or is block by large object.

The TRAINING SCREEN has 6 COMMAND buttons. There are 3 TONE COMMAND buttons for positive behavioral training and 3 STIMULUS buttons to deter unwanted or dangerous behaviors. When you press a Tone Command or Stimulus button the button will enlarge and turn yellow while the phone waits for the collar to acknowledge the command. The STATUS BOX will also turn yellow and display “Command Sent” Command status messages, which are unique to the TRAINING screen are shown below.



When the phone receives an acknowledgement from the collar that the command was received the command button will return to normal size and turn green indicating a successful transmission. The STATUS BOX will also turn green and display the message “Command Received”. If the your phone does not receive an acknowledgement within 2 seconds the COMMAND BUTTON will turn red. The STATUS BOX will also turn red and display the message “Command Failed”. Command failures within the working range are rare but, may be caused by a large metal object, like a car, coming between the collar and phone or a lot of radio frequency noise in the area.

The COMMAND BUTTON and STATUS BOX will remain in their post command state, reminding you of your last action, until you select another command or exit the TRAINING screen.

Command Status

COMMAND SENT

Phone as sent command to collar and is waiting for acknowledgement.

COMMAND
RECEIVED


Command was received and acknowledged by collar.

COMMAND FAILED

Collar did not acknowledge command. (This is usually followed by a “LINK LOST” message.

SETTING UP A CUSTOM STIMULUS PROFILE

You may set up a unique stimulus profile for each collar by pressing the SETTINGS link at the top right in the MENU BAR. This will take you to the FIND DOGS screen. At the bottom left of the FIND DOGS screen press the Setup Stimulus button.




Setup Stimulus button on FIND DOGS screen brings you to the STIMULUS INTENSTIY setup screen



This takes you to the STIMULUS INTENSITY screen.

You may set a custom intensity for each of the 3 STIMULUS buttons on the TRAINING screen with the SLIDER BARS. Each SLIDER BAR allows you to adjust the stimulus intensity for the numbered STIMULUS button as a percentage of max intensity. Click the SAVE button to save your settings. Pressing the DEFAULTS link at top right in the MENU BAR will return the settings to the factory defaults. Pressing the NEXT button, at the bottom right, will display the STIMULUS DURATION screen. In addition to allowing you to customize the intensity of each stimulus button, Bluefang collars are the only dog training collars that also let you set the duration of each stimulus correction. The SLIDER BARS on the STIMULUS DURATION screen allow you to set the time each correction lasts from 1/10 sec. to 2 sec. Adjust the sliders to the desired stimulus durations and press SAVE. Again, the DEFAULTS link at the top right in the MENU BAR returns the sliders to the factory default settings. To return to the TRAINING screen press the BACK link at the top left in the MENU BAR. This takes you back to the STIMULUS DURATION screen. Press the BACK link again. This returns you to the FIND DOGS screen. Pressing the TRAIN link at the top left will return you to the TRAINING screen. Complete training instructions are found in the HOW TO TRAIN YOUR DOG SECTION. The BF-22 allows you set up unique stimulus profiles for an unlimited number of collars.

Bark Control Screen



Access the Bark Control Screen by selecting STOP MY DOG'S BARKING on the MAIN MENU screen. This screen has the STATUS BOX just like the TRAINING screen. Also like the TRAINING screen, the name of the collar is displayed above the status box. The BARK CONTROL screen allows you to turn on the bark control feature by tapping the BARK CONTROL ENABLED button. You may also select the Bark Detect MODE and STIMULUS output type.

Bark detect modes

STOP NUISANCE BARKING - Triggers only on slower, nuisance type of barking and allows the more rapid barking that a dog exhibits when barking at an intruder or emergency.

STOP ALL BARKING - Collar triggers on all detected barks

STOP BARKING AND HOWLING - Triggers on all detected barks and howling.

Bark Control Settings




Clicking the SETTINGS link in the MENU BAR at the top right displays the FIND DOGS screen where you can connect to and name your collar. At the bottom right of the FIND DOGS screen, click the SET-UP STIMULUS link to display the BARK CONTROL SETTINGS screen. This screen allows you to set the sensitivity of the bark detection. Your collar's factory presets are effective for most dogs. However, if your collar seems to trigger too easily or fails to detect all barks, you may need to manually fine tune the sensitivity to your dog's voice.

BARK DETECT LEVEL SLIDER - If your dog has a quiet bark move the slider to the right, toward a higher percentage of

total detection sensitivity. If your dog has a loud bark move it more toward the left.

DOG SIZE SLIDER - This slider fine tunes the collar to the pitch of your dog's voice. Large dogs have deeper voices, smaller dogs have more high pitched voices. A small dog will weigh just a few pounds. A large dog will weigh 100 lbs. or more. Adjust the DOG SIZE slider to the relative size of your dog.



Containment

The model BF-22 has the ability to act as an electronic fence. Access the electronic FENCE screen from the MAIN MENU by pressing the CONTAIN MY DOG button. The FENCE screen allows you to turn the containment feature on and off. When you turn containment on, your collar will act as an electronic fence receiver that will work with any High Tech Pet electronic fence transmitter. Tap the ELECTRONIC

FENCE switch to enable the containment feature. Note that for BF-16 models, the Electronic Fence switch is not functional.

Firmware Update feature



The most unique and useful feature of your Bluefang collar is something you won't notice right away. However, it will allow your collar to grow and change with new features and functions as they become available from the developers at High Tech Pet. When your collar connects, the app checks the collar to make sure it has the latest firmware. If there is a newer one available, the app will ask if you wish to download it.

If The the app gets the latest firmware from our online server and wirelessly transfers it to the collar. Don't be surprised if you notice new and useful features that take advantage of the advanced hardware in your Bluefang collar.

Principles of positive behavioral training

Your Bluefang collar is designed around High Tech Pet's proprietary Command - Tone - Stimulus™ training system that uses positive tones as both command and reward. To teach your dog a positive behavior, you will need a short training lead on a separate restraining collar. For initial training you will need some dog treats. The process of behavioral training will associate the TONE COMMAND emitted by the Bluefang collar with a verbal command such as Sit, Stay or Heel. It will also be associated with the reward.

STEP 1: Decide the verbal command and the TONE COMMAND button to be used, for example, "Sit" and TONE COMMAND button 1.

STEP 2: Say the verbal command and activate the associated tone while demonstrating the behavior. For "Sit", Say "Sit" and gently pull up on the training lead while pushing down on your dog's hind section manipulating him into a sitting position.

STEP 3: Administer the reward by saying "Good Dog" and again

activating the tone. Pet your dog and give him a treat. Repeat these steps until your dog performs the behavior on his own. When he performs the command easily you may remove the treat but continue to use the tone as a reward, say “Good Dog” and pet him after he performs the command.

Keep your training sessions to no more than 15 minutes long and no more than 2 or 3 times per day. Patience is the key to a successful training experience. Don't lose patients with your dog. Keep to tone of your voice positive, stress free and encouraging.

How to use negative stimulus

Negative stimulus (shock) may be useful in deterring unwanted and dangerous behavior. Bear in mind that even though the stimulus CANNOT cause any physical injury to your dog, it does cause a painful sensation and should be used sparingly and humanely. Stimulus Level 1 should be set to the minimum amount of Intensity and duration that your dog perceives. When triggered, your dog should show a perceptible but minimal reaction to the stimulus, such as perking his ears. This very mild stimulus level may be used merely to get your dog's attention if he gets distracted during a training session. It may also be used as a warning of a more intense stimulus to come if he continues an undesirable behavior such as digging, jumping or chewing.

Stimulus Level 2 should be adjusted to a slightly more intense level. We recommend 20% higher in intensity than level 1 and a duration of approximately .5 seconds. This stimulus level should be used along with a stern “No” command to stop unwanted behaviors. Remember, that you are teaching your dog to discontinue natural behaviors. Dogs naturally love to dig and chew. Teaching your dog that this does not apply to the garden and your favorite furniture must be done with patience and kindness.

Stimulus Level 3 is reserved for stopping behaviors that pose a threat to your dog or others, such as chasing cars or people, biting or fighting with other dogs. This level should be set to intense and used rarely in emergencies only.

Your Bluefang collar has a safeguard that allows you to apply no more than 5 stimulus corrections within a 30 second period. If you try to exceed that number the stimulus will automatically be disabled for 30 seconds.

IMPORTANT CAUTION NOTES:

Aggressive Dogs: Do not use the corrective stimulus feature on dogs known to be or could become aggressive. Note that animals are unpredictable. You should be aware of your dog's temperament and use only the mildest stimulus at first to make sure you dog does no react aggressively to the stimulus.

Skin Irritation: Although, it is impossible for the stimulus of a Bluefang collar to cause any skin or organ damage, any collar with probes can cause skin irritation in a small percentage of dogs which, if left unchecked can lead to infection. Check your dog's neck daily for redness or sores.

Bluefang[®]

Biting Edge Technology[™]

Exclusively by



Engineered in the USA
by High Tech Pet Products, Inc.
2476 Palma Drive, Ventura, CA 93003
www.HighTechPet.com

Components Manufactured at High Tech Pet's Shenzhen, China facility.
Assembled and tested in USA.