



Z-Wave Protocol Implementation Conformance Statement

LED Dimmer Z-Wave 200W

General Information

Product Identifier: 1402756
Brand Name: Namron
Product Version: HW: 1 FW: 1.17
Z-Wave Certification #: ZC10-20036893

Product Features

Controller Supports Multiple Z-Wave Interfaces No
Controller Supports Multiple Networks No

Z-Wave Product Information

Supports Z-Wave Beaming Technology? Yes
Supports Z-Wave Network Security? Yes
Supports Z-Wave AES-128 Security S0? Yes
Supports Security S2? Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible? Yes

Z-Wave Technical Information

Z-Wave Frequency: CEPT (Europe)
Z-Wave Product ID: 0x0001
Z-Wave Product Type: 0x0202
Z-Wave Hardware Platform: ZM5101
Z-Wave Development Kit Version: 6.81.03
Z-Wave Library Type: Enhanced 232 Slave
Z-Wave Device Type / Role Type: Light Dimmer Switch / Always On Slave

Association Group Information

Group # / Max **Description**

Nodes

1 / 5 The ASSIC or Lifeline:4C 69 65 6C 69 6E 65 1.when press and hold down Reset button over 5s to reset the dimmer send"Device Reset locally Notification CC" to associated devices of this group to report factory reset

Z-Wave Protocol Implementation Conformance Statement

(Continued)

LED Dimmer Z-Wave 200W

Supported Command Classes (15):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Powerlevel
Security S0	Security S2
Supervision	Switch Multilevel V2
Transport Service V2	Version V2
Z-Wave Plus Info V2	