



Reading the display




Countdown alarm operation



Setting daily alarm

If the daily alarm is set, the beeper sounds for 20 seconds at the preset time every day until cleared. To stop the beeper, press any button. If the time signal is set, the watch sounds every hour on the hour with a "Be-e-op" signal.
(Sound demonstration) Press and hold the (A) button in alarm mode to sound the beeper.




Press **(B)** in the daily alarm mode to set hours and minutes.
Each press of **(A)** advances the alarm setting by 1 hour.


Press **(B)** to set minute digits. Each press of **(A)** advances the alarm setting by 1 minute.

* If the **(C)** button is pressed, the watch reverts to the regular timekeeping mode. (Quick digit advance) When the **(A)** button is pressed for more than 2 seconds, the digit advances quickly. When released, digit advance will stop.

[ON or OFF setting of daily alarm and time signal]



Stopwatch operation




A signal confirms start/stop operation.
(Working range) The stopwatch display is limited to 59 minutes 59.9 seconds. For longer times, reset and start again.

(a) Net time measurement




SU: Sunday MO: Monday TU: Tuesday WE: Wednesday TH: Thursday FR: Friday
SA: Saturday



Setting time and calendar

1. In the time setting mode, first press (A) on a time signal to correct seconds.
2. Press (B) to shift flashing position. The digit(s) to be changed will flash.



3. Each press of (A) advances the setting by one. Keep pressed for quick advance.
4. Press (C) to complete setting.

Specifications

Accuracy at normal temperature: ± 30 seconds per month

Display capacity:

- Regular timekeeping mode
 - Hour, minute, second, am/pm, month, date, day (double display)
- Calendar system: Auto-calendar (set at 28 days for February)
- Countdown alarm mode
 - Input range: 1 to 30 minutes
- Daily alarm
- Hourly time signal
- Stopwatch mode
 - Measuring capacity: 59 minutes 59.9 seconds
 - Measuring unit: 1/10th of a second
 - Measuring modes: Net time

Battery:	Battery type	Battery life*
	CR1216	Approx. 2 years

* Includes an average of 20-second alarm per day.