



Z-Wave Protocol Implementation Conformance Statement

In-Wall Smart Toggle Switch

General Information

Product Identifier: 14319/46563/ZW4009
Brand Name: Jasco
Product Version: HW: 255 FW: 5.53
Z-Wave Certification #: ZC10-19056492

Product Features

Firmware Updatable Updatable by Consumer by RF
Neutral Wire Required Yes
Z-Wave Scene Type Central Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology? Yes
Supports Z-Wave Network Security? Yes
Supports Z-Wave AES-128 Security S0? No
Supports Security S2? Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible? Yes

Z-Wave Technical Information

Z-Wave Frequency: U.S. / Canada / Mexico
Z-Wave Product ID: 0x3138
Z-Wave Product Type: 0x4952
Z-Wave Hardware Platform: ZM5202
Z-Wave Development Kit Version: 6.81.03
Z-Wave Library Type: Enhanced 232 Slave
Z-Wave Device Type / Role Type: On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max **Description**
Nodes

Z-Wave Protocol Implementation Conformance Statement

(Continued)

In-Wall Smart Toggle Switch

- 2 / 5
- Supports Basic Set and is controlled by pressing the ON or OFF button with the local load.
- 3 / 5
- Supports Basic Set and is controlled by double pressing the ON or OFF button.

Supported Command Classes (18):

Application Status	Association Group Info
Association V2	Basic V2
Central Scene V3	Configuration V4
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Powerlevel
Scene Activation	Scene Actuator Conf
Security S2	Supervision
Switch Binary V2	Transport Service V2
Version V3	Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic V2
