



品牌：闪魔  
部门：品牌市场部-品牌视觉组  
名称：E07真无线蓝牙耳机英文说明书  
日期：202.07.04  
设计：胡可  
版本：V2  
供应商：




Instruction Manual

An innovative design brand of digital


www.smartdevil.com




E07 True Wireless Bluetooth Earbuds




E07 True Wireless Bluetooth Earbuds




An innovative design brand of digital




www.smartdevil.com




Charging Case




E07 True Wireless Bluetooth Earbuds




Earbuds Tips




Lanyard




Manual




Type-C Charging Cable




① Touch Control Area  
② Microphone  
③ Earbuds Tip




④ Charging Contacts  
⑤ L/R Logo  
⑥ Sound Output



① Type-C Charging Port  
② Lanyard Hole






Power On


1. Open the charging case, and the earbuds will automatically turn on while taking out.

2. With the earbuds off, long press the unilateral touch area of the earbud for 5s to turn on.




Power Off

The earbuds automatically turn off after being put back in the charging case.




Bluetooth Pairing

1. Open the charging case, and the earbuds will automatically enter the pairing mode while taking out. Activate the Bluetooth setting on your phone, with selecting "SmartDevil E07" in the Bluetooth list of the phone to complete the pairing. If no device is connected for more than 5 minutes or the connection is invalid, it indicates that the pairing fails and the earphone will automatically shut down.




2. After the first successful pairing, the earbuds will automatically save the Bluetooth information of the device. The next time you use the earbuds, you can open the charging case and take out the earbuds with automatic reconnection to the last paired device. Note: After successful Bluetooth pairing, both the left and right earbud can be used individually in one ear.




Game Mode

Four or five clicks on either side of the earbud can activate or close the game mode, and the earbud can return to the normal mode after being put back in the charging case.




FCC ID: FCC ID:2BBOM-E07




FCC


This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:  
- Recient or relocate the receiving antenna.  
- Increase the separation between the equipment and receiver.  
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.  
- Consult the dealer or an experienced radio/TV technician for help.  
This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:  
(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.




Scan and follow SmartDevil official website




Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment



\* RF warning for Portable device:  
The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.




●Shenzhen SmartDevil Digital Technology Co., Ltd.●Address:Floor 4-6, Building C, No.10,EastDistrict,ShangxueScienceand Technology Park,BantianStreet,LonggangDistrict,Shenzhen.●PhoneNumber: +86 0755-83746007




Connection exception and handling method


1. Bluetooth effective distance is 10 meters. Beyond the range of effective distance, the earbuds and the connected device will be automatically disconnected. Enter the effective distance range again within 5 minutes, and the Bluetooth will automatically reconnect. Otherwise, the earbuds will automatically shut down. To reconnect, follow the "Bluetooth Pairing" steps (see P4-5).

2.If the earbud device cannot be searched or the connection times out, try the following methods:  
(1) Check whether the insulating protective film between the charging case and the earbuds has been removed;  
(2) Confirm whether the earbud is turned on and in pairing mode;  
If the connection fails after the above two points are excluded, you can long press the left and right earbuds for 8 seconds to clear the paired information, and then connect Bluetooth after the earbuds re-enter the pairing mode.







Music Mode




Play/Pause




Next track




Previous track




Double-tap Rearbud




Triple-tap Rearbud




Triple-tap L earbud




Call Mode




Answer a call




End a call




Reject an incoming call




Cancel dialing




Double-tap L/R




Double-tap L/R




Double-tap L/R 3s




Double-tap L/R




Voice Activation




Siri or other voice assistants




Game Mode




Reset




Double-tap L earbud




Tap 4/5 times L/R




Long press L and R 8s at the same time




Prompt Tone




In Pairing




Bluetooth connection successful




Call Reminder




Low Battery




Connecting




de lei




Consistent with your mobile phone ringtone prompt




bo




SmartDevil E07




1. Earbud power display: After the earbud is connected to the Bluetooth of the phone, the status bar of the mobile phone usually displays the remaining power.




2. Earbud low battery reminder: When the earbud battery is below 10%, the earbud will issue a warning every 5 minutes until it powers off. After hearing the warning, please return the earbud to the charging case and charge it as soon as possible.




3. Charging case power display:



(1) <25% battery: The green light of the charging case flashes and goes off 4 seconds later, indicating that the battery is below 25%. Please charge the charging case immediately.




(2) The green light of the charging case is steady on for 4 seconds, indicating that the power level is between 25% and 100%. At this time, the charging case can charge the earbuds 1 or 2 times.




1.Earbuds Charging

Put the earbuds into the charging case, and the white light of the earbuds flashes for 10s at the same time with the earbuds entering the charging state.




2.Charging Case Charging

It is recommended to use a standard 5V/1A adapter and the Type-C charging cable that comes with the product to charge the case. When charging, the white light flashes, and when the battery is 100%, the white light is steady on.




●Charging Instructions




Status

LED Indicator




Low Battery

When the charging case battery is below 25%, the green light flashes and goes off 4 seconds later.




Charging

When charging, the white light flashes.  
When the battery is 100%, the white light is always on.




●Basic Parameter


Device Name	SmartDevil E07
Sound Unit	6mm, compounded PU film
Frequency Range	20Hz-20KHz
Microphone Sensitivity	-38±1dB
Audio Decoding	AAC/SBC
Bluetooth Version	5.3
Bluetooth Distance	10m
Battery Type	Lithium-ion Battery
Battery Capacity	400mAh (Earbuds) 320mAh (Charging Case)
Battery Life	(30% volume) Earbuds 7H Charging Case 19H
Charging Time	Earbuds 0.5H/Charging Case 1.5H
Charging Input	DC 5V --- 1A
Charging Port	Type-C




Note: All specifications and parameters are derived from the SmartDevil Lab. The battery capacity, battery life and charging time are obtained by using the standard SmartDevil charger at room temperature (25℃) in the SmartDevil Lab. The actual data may be slightly different due to different usage environments and chargers.




●Attentions




1.Please do not place the product which contains small parts in the place where children can reach, in case of choking risk after swallowing.




2. This product is not a toy. Children under 3 years old are prohibited from using the product, and Children aged 3 and up need to use this product under adult.




3. For the sake of safety, please do not use this product during driving or riding to drive safely in strict compliance with traffic regulations.




4. Do not use this product at high volume for a long time to prevent hearing damage. If you have ear discomfort or tinnitus, stop using immediately and seek medical attention.




5. Please do not immerse the product in water because the charging case is not waterproof. And do not continue to use it in case of liquid splashing, rain wetting or dampness.




6. In the dry season, users may feel tingling when wearing or touching the product due to static electricity, rather than equipment damage.




●Battery safety warning




1.Please use the product with a built-in lithium battery in the temperature range of 0℃ to 40℃, in case of product failure with too high or too low temperature.



2. Do not place the product in high temperature sunlight for continuous exposure. Keep the product away from heat source or fire source and so on high temperature environments.



3. Non-professional person are forbidden to disassemble, replace or modify the battery, in case of fire and even the total product damage.



4. Do not knock, impact, squeeze or put the product into the fire, so as not to cause explosion and other dangers. If the product expands, do not continue to use.

尺寸：展开480\*80mm 成品80\*80mm  
材质：80g哑粉  
工艺：1C 风琴折