porodo | CHOOSE THE BEST

PORODO WATCH 8+

USER MANUAL

PD-SW8PALU

Thank you for choosing our product! To have a comprehensive understanding and using this device, to know all the features and simple operation method, please read this manual first. The functions on the user manual may be little different with physical, please make the final products as the standard. The typing errors in this manual and discrepancies will be timely updated with the latest products. If we have updates, this manual will be subject to change without notice. Our company reserves the right of final interpretation.

Package:
Gift box- x1
User manual- x1
Smart band unit- x1
Charger- x1

Remark:

- This product has a built-in rechargeable lithium battery. Safety warnings for battery use: do not disassemble, strike, squeeze or put into fire; if it is severely swollen, do not continue to use it; do not place it in a high temperature environment; do not use the battery after it is immersed in water.
- Do not use it when have a hot shower/bath or sauna, the vapors will get into the host, scratch damage of peripheral components. All these are beyond the scope of the warranty.
- This product is not a medical device. The health data and suggestions provided are for reference only, not as a basis for diagnosis and treatment.

Operation Guide:

Upper crown:
Scroll to zoom in/out the smart menu, or switch the watch faces, tap enter the main menu, double tap to switch the menu style.

Bottom button:
Hold the button to ON/OFF the device; short press the button to light the screen when screen off.

Touch instructions:
Tap to enter each function, swipe right to return; At home page swipe down to enter the status bar, swipe up to the notification center, slide left to enter the favorite functions, swipe to the + add favorite functions. swipe right to main menu.

Touch Instruction:

Watch face switch
Watch face switch: hold the home screen to change the different watch faces.

Watch band
Watch strap change: Pull forward the strap to any sides, watch strap can be easily taken apart.

Charging instruction:
This product adopts a wireless charger that supports mobile phone chargers within 5V and computer USB port. Put the watch on the charging puck and it will automatically charge. A full charge takes about 3 hours.

Connection:
Watch connects to Phone, download the App in the Phone at very first, reference following 2 methods.

MActive Pro

1) Android/IOS Phone: Scan following QR code image by browsers or by any Scanner to Download.
After installation, turn on phone Bluetooth and App, confirm the notifications and all others permission App asks are enabled, and fill up personal information. Tap "Add device", search "PD-SW8PALU" device (turn on the GPS in the smart phone before binding) and tap connect.

Message Settings:
In App —, Device - Notifications, select the corresponding Apps, turn ON the switch.

What if I don't get the notice?
1. The watch's notification only synchronous phone notifications from notification center, such as incoming calls, SMS, WhatsApp, WeChat etc., if the phone doesn't receive notifications in notification center, then the watch cannot receive them either, it must set as phone able to receive notifications of the corresponding Apps, turn ON the notification permission in phone setting.

2. If still not receiving any notification after step (1). Reset the watch to factory setting, enter the Bluetooth settings in the phone, and check if it's connected device has "PD-SW8PALU". If so, please unpair, turn OFF the phone's Bluetooth, then turn it ON again to reconnect.

3. If all above 2 steps cannot solve the notification issue, uninstall the App and download it again. Remember agree all permissions App asks when the installation done and very beginning turn the App on, and then reconnect again.

Main Features:

Firmware upgrade:
As Bluetooth connected, in App, Tap "Device- "Firmware version"- it will remind you if there's a new version available for update. During the updating, it will show a process bar, wait it until complete. Watch will restart and reconnect the phone App. Do not operate the watch during the update. It takes 3-5 mins.

Call:
This device supports Bluetooth calls, and the watch controls the phone to make or receive calls. Tap the Bluetooth call icon in the drop-down menu, in phone-Settings-Bluetooth -search for "Por Watch 8+" and connect to watch. The Bluetooth call audio can be turned off, then watch cannot make or receive Bluetooth calls, and the low power consumption mode is turned on by default, which can extend the use time.

Phonebook:
After connected to the phone App, you can add 10 frequently used contacts to the watch phonebook from the App.

Language/Time/Date:
Synchronizing of language/date/time between the mobile phone and the Smart Watch after being connected.

Standby watch faces:
There are couples of watches faces for options, long press 3 seconds at home screen to switch different watch faces; also allows download new watch faces in the App; it is able to customize your photos as watch face background.

Sleep monitor:
Sleep monitoring will be automatically active from 10:00pm to 8:00am the next day. You can check the details of sleep quality with the app in the phone.

Notifications:
Synchronizing and display of app notifications such as Facebook, WhatsApp, SMS, Email etc., between the mobile phone and the Smart Watch. Up to 8 notifications can be displayed on the watch. Please adjust the settings in the "MActive Pro" app and allow notifications to be displayed (app permissions). It is able to decline incoming calls via watch.

Activity info:
Showing the workout and health data including Steps, Distance, Calorie's consumption. This data will be saved until midnight (12:00 am) every day and then reset to 0 values for coming day. You can look up previous data in History.

Exercise:
Select a sport mode to record your workout. Enter to start the activity, slide right to pause the workout, tap to end the workout. It records the duration, calories, heart rate etc.

Heart Rate Monitoring Function:
When this function is activated, the heart rate is being measured by the device scanning the surface capillary of the skin with green optical diodes. Please allow for about 2 seconds to start measuring and recording. Slide to other menus to stop measuring. Please refer to information about average heart rate, heart rate while exercising for your age group and gender online and/or ask your medical practitioner for advice. (Please note: The device is not a medical device. Any values shown are for reference only.)

Stopwatch Function:
Press the start and pause, again press for stop.

Remote Control (Music):
Allows to activate and control music playback on the phone via the Smart Watch (a music playback app should be installed on the phone).

About:
Check model number, Bluetooth address, version number.

Reset: Tap to reset all data (factory mode).

Alarm Function:
You can set several alarm times via the "MActive Pro" app on the phone.

Sedentary, drink reminder:
Via the App set a time for exercise and/or a reminder to drink.

Find Phone Function:
As the device and phone are connected, the Find Phone Function can support locating your mobile phone. Tap "Find Phone" and locate your phone via the ringtone/sound coming from your phone.

Wrist Wakeup:
You can "wake up' the watch with wrist movement. Please set this function with the app. Please note that this might increase power consumption.

Female Period:
Set your own period time, better remind to manage your health.

For more information, please contact our support team:
support@porodo.net

Made in China

www porodo net /porodo /myporodo

porodo | CHOOSE THE BEST

PORODO WATCH 8+

دليل اللاستخدام

PD-SW8PALU

شكرًا لك لاختيار منتجاتنا! للحصول على فهم شامل واستخدام هذا الجهاز ، لمعرفة جميع الميزات وطريقة التشغيل البسيطة ، يرجى قراءة هذا الدليل أولاً. قد تختلف الوظائف الموجودة في دليل المستخدم قليلاً عن الوظائف المادية ، يرجى جعل المنتجات النهائية هي المعيار.

سيتم تحديث أخطاء الكتابة في هذا الدليل والاختلافات في الوقت المناسب بأحدث المنتجات. إذا كانت لدينا تحديثات ، فسيخضع هذا الدليل للتغيير دون إشعار. تحتفظ شركتنا بحق التفسير النهائي.

الطرد
صندوق هدايا- ١
دليل المستخدم- ١
وحدة السوارالذكي- ١
شاحن- ١

ملاحظة:

- يحتوي هذا المنتج على بطارية ليثيوم مدمجة قابلة لإعادة الشحن. تحذيرات السلامة لاستخدام البطارية: لا تفككها أو تضربها أو تضغط عليها أو تشعل النار فيها ؛ إذا كان منتفخًا بشدة ، فلا تستمر في استخدامه ؛ لا تضعه في بيئة ذات درجة حرارة عالية ؛ لا تستخدم البطارية بعد غمرها في الماء.
- لا تستخدمه عندما يكون لديك دش ساخن / حمام أو ساونا ، ستدخل الأبخرة إلى المضيف ، مما يؤدي إلى خدش تلف المكونات الطرفية. كل هذه خارج نطاق الضمان.
- هذا المنتج ليس جهاز طبي. البيانات الصحية والاقتراحات المقدمة هي للإشارة فقط ، وليس كأساس للتشخيص والعلاج.

دليل العمليه:

القمة العلوية:
قم بالتمرير لتكبير / تصغير القائمة الذكية ، أو تبديل وجوه الساعة ، انقر فوق الدخول إلى القائمة الرئيسية ، وانقر نقرًا مزدوجًا لتبديل نمط القائمة.
الزر السفلي:
استمر في الضغط على الزر لتشغيل / إيقاف تشغيل الجهاز ؛ قصير اضغط على الزر لإضاءة الشاشة عند إيقاف تشغيل الشاشة.
تعليمات اللمس:
انقر لإدخال كل وظيفة ، واسحب لليمين للعودة ؛ في الصفحة الرئيسية ، اسحب لأسفل للدخول إلى شريط الحالة ، واسحب لأعلى إلى مركز الإشعارات ، ثم مرر لليسار للدخول إلى الوظائف المفضلة ، واسحب إلى + إضافة وظائف مفضلة. انقر لليمين إلى القائمة الرئيسية.

تعليمات اللمس:

واجهة الساعة
واجهة الساعة: اضغط باستمرار على الشاشة الرئيسية لتغيير وجوه الساعة المختلفة.

حزام الساعة
تغيير حزام الساعة: اسحب الحزام للأمام إلى أي جانب ، ويمكن تفكيك حزام الساعة بسهولة.

تعليمات الشحن:
يستخدم هذا المنتج شاحنًا لاسلكيًا يدعم شواحن الهواتف المحمولة بجهد ٥ فولت ومنفذ يو أس بي للكمبيوتر. ضع الساعة على قرص الشحن وسيتم شحنه تلقائيًا. يستغرق الشحن الكامل حوالي ٣ ساعات.

اتصال:
الساعة تتصل بالهاتف ، قم بتنزيل التطبيق في الهاتف في البداية ، قم بالرجوع إلى الطريقتين التاليتين

MActive Pro

١) هاتف Android / IOS: امسح صورة رمز الاستجابة السريعة التالية بواسطة المتصفحات أو بواسطة أي ماسح ضوئي للتنزيل.
بعد التثبيت ، قم بتشغيل تطبيق بلوتوث والتطبيق للهاتف ، وتأكد من تمكين الإشعارات وجميع طلبات الأذونات الأخرى التي يطلبها التطبيق ، واملأ المعلومات الشخصية. اضغط على "إضافة جهاز" ، وابحث عن جهاز "PD-SW8PALU" (قم بتشغيل GPS في الهاتف الذكي قبل الربط) وانقر فوق اتصال.

إعدادات الرسالة:
في التطبيق :- الجهاز - الإشعارات ، حدد التطبيقات المقابلة ، قم بتشغيل المفتاح.

ماذا لو لم أحصل على الإشعار؟
١. إشعار الساعة فقط إشعارات الهاتف المتزامنة من مركز الإشعارات ، مثل المكالمات الواردة والرسائل القصيرة و WhatsApp و WeChat وما إلى ذلك ، إذا لم يتلق الهاتف إشعارات في مركز الإشعارات ، فلن تتمكن الساعة من استلامها أيضًا ، فيجب تعيينها على أنها الهاتف قادر على تلقي إشعارات التطبيقات المقابلة ، قم بتشغيل إذن الإعلام في إعداد الهاتف.

٢. إذا استمر عدم تلقي أي إشعار بعد الخطوة (١). أعد ضبط الساعة على إعداد المصنع ، وأدخل إعدادات بلوتوث في الهاتف ، وتحقق مما إذا كان الجهاز المتصل به "PD-SW8PALU". إذا كان الأمر كذلك ، فالرجاء إلغاء الإقران وإيقاف تشغيل بلوتوث في الهاتف ، ثم تشغيله مرة أخرى لإعادة الاتصال.

٣. إذا لم تتمكن الخطوتان أعلاه من حل مشكلة الإشعار ، فقم بإلغاء تثبيت التطبيق وتنزيله مرة أخرى. تذكر الموافقة على جميع الأذونات يسأل التطبيق عند انتهاء التثبيت والبدء في تشغيل التطبيق ، ثم إعادة الاتصال مرة أخرى.

الخصائص الرئيسية:

ترقية البرامج الثابتة:
أثناء اتصال البلوتوث ، في التطبيق ، انقر على "إصدار البرنامج الثابت للجهاز" - سيذكرك إذا كان هناك إصدار جديد متاح للتحديث. أثناء التحديث ، سيعرض شريط العملية ، انتظر حتى اكتماله. ستتم إعادة تشغيل الساعة وإعادة توصيل تطبيق الهاتف. لا تقم بتشغيل الساعة أثناء التحديث ، فالأمر يستغرق من ٣-٥ دقائق.

مكالمة:
يدعم هذا الجهاز مكالمات بلوتوث ، وتتحكم الساعة في الهاتف لإجراء المكالمات أو استقبالها. انقر على رمز اتصال البلوتوث في القائمة المنسدلة ، في إعدادات الهاتف ، ابحث عبر البلوتوث عن "Por Watch 8+" واتصل بالساعة. يمكن إيقاف تشغيل صوت مكالمة بلوتوث ، ثم يتعذر على الساعة إجراء مكالمات بلوتوث أو استقبالها ، ويتم تشغيل وضع استهلاك الطاقة المنخفض افتراضيًا ، مما قد يؤدي إلى إطالة وقت الاستخدام.

سجل الهاتف:
بعد الاتصال بتطبيق الهاتف ، يمكنك إضافة ١٠ جهات اتصال مستخدمة بشكل متكرر إلى دليل هاتف الساعة من التطبيق.

اللغة / الوقت / التاريخ:
مزامنة اللغة / التاريخ / الوقت بين الهاتف المحمول والساعة الذكية بعد الاتصال.
وجوه ساعة الاستعداد:
هناك أرواح من وجوه الساعات للحصول على خيارات ، اضغط لفترة طويلة ٣ ثوانٍ على الشاشة الرئيسية لتبديل وجوه الساعة المختلفة ؛ يسمح أيضًا بتنزيل وجوه ساعة جديدة في التطبيق ؛ إنه قادر على تخصيص صورك كخلفية لوجه الساعة.

مراقب النوم:
سيتم تنشيط مراقبة النوم تلقائيًا من الساعة ١٠:٠٠ مساءً حتى ٨:٠٠ صباحًا في اليوم التالي. يمكنك التحقق من تفاصيل جودة النوم من خلال التطبيق الموجود بالهاتف.

إشعارات:
مزامنة وعرض إشعارات التطبيقات مثل Facebook و WhatsApp و SMS والبريد الإلكتروني وما إلى ذلك ، بين الهاتف المحمول والساعة الذكية. يمكن عرض ما يصل إلى ٨ إشعارات على الساعة. يرجى ضبط الإعدادات في تطبيق "MActive Pro" والسماح بعرض الإشعارات (أذونات التطبيق). إنه قادر على رفض المكالمات الواردة عبر الساعة.

معلومات النشاط:
عرض بيانات التمرين والصحة بما في ذلك الخطوات والمسافة واستهلاك السعرات الحرارية. سيتم حفظ هذه البيانات حتى منتصف الليل (١٢:٠٠ صباحًا) كل يوم ثم إعادة تعيينها إلى ٠ قيم لليوم التالي. يمكنك البحث عن البيانات السابقة في المحفوظات.

ممارسه الرياضه:
حدد وضع الرياضة لتسجيل التمرين. أدخل لبدء النشاط ، مرر لليمين لإيقاف التمرين مؤقتًا ، انقر فوق لإنهاء التمرين. يسجل المدة والسعرات الحرارية ومعدل ضربات القلب وما إلى ذلك.

وظيفة مراقبة معدل ضربات القلب:
عندما يتم تنشيط هذه الوظيفة ، يتم قياس معدل ضربات القلب بواسطة الجهاز الذي يقوم بمسح الشعيرات الدموية السطحية للجلد باستخدام الثنائيات الضوئية الخضراء. يُرجى الانتظار لمدة ثانيتين تقريبًا لبدء القياس والتسجيل. قم بالتمرير إلى القوائم الأخرى لإيقاف القياس. يرجى الرجوع إلى المعلومات المتعلقة بمتوسط معدل ضربات القلب ومعدل ضربات القلب أثناء ممارسة الرياضة بالنسبة لفئتك العمرية والجنس عبر الإنترنت و / أو استشر طبيبك للحصول على المشورة. (يرجى ملاحظة: الجهاز ليس جهازًا طبيًا. أي قيم معروضة هي للإشارة فقط.)

وظيفة ساعة التوقيف:
اضغط على البداية والإيقاف المؤقت ، واضغط مرة أخرى للإيقاف.

جهاز التحكم عن بعد (موسيقى):
يسمح بتنشيط تشغيل الموسيقى والتحكم فيه على الهاتف عبر Smart Watch (يجب تثبيت تطبيق تشغيل الموسيقى على الهاتف).

حول:
تحقق من رقم الطراز وعنوان بلوتوث ورقم الإصدار.

إعادة التعيين: انقر لإعادة تعيين جميع البيانات (وضع المصنع).

وظيفة المنبه:
يمكنك ضبط عدة مرات منبه عبر تطبيق "MActive Pro" على الهاتف.

تذكير الشرب:
عبر التطبيق ، حدد وقتًا لممارسة الرياضة و / أو تذكيرًا بالشرب.

البحث عن وظيفة الهاتف:
نظرًا لأن الجهاز والهاتف متصلان ، يمكن أن تدعم وظيفة البحث عن الهاتف تحديد موقع هاتفك المحمول. انقر على "Find Phone" وحدد موقع هاتفك عبر نغمة الرنين / الصوت القادم من هاتفك.

تنبيه المعصم:
يمكنك "إيقاظ" الساعة بحركة المعصم. يرجى تعيين هذه الوظيفة مع التطبيق. يرجى ملاحظة أن هذا قد يزيد من استهلاك الطاقة.

الفترة الأنثوية:
حدد وقت الدورة الشهرية ، وتذكير بشكل أفضل بإدارة صحتك

لمزيد من المعلومات ، يرجى الاتصال بفريق الدعم لدينا:
support@porodo.net

Made in China

www porodo net /porodo /myporodo