

PYLE
PyleUSA.com



VISIT US ONLINE:
Have a question?
Need service or repair?
Want to leave a comment?
PyleUSA.com/ContactUs

PYLE

Questions? Issues?

We are here to help!

Phone: (1) 718-535-1800

Email: support@pyleusa.com




PT6060CHAE

6 Channel Wireless BT Home Theater Amplifier

Built-in Cooling Fan with & Radio Antenna,
BT/FM/Optical/Coaxial/HDMI & Dual 10 Band EQ,
2000 Watts Peak Power


Front and Back Panel



- | | |
|---|--------------------------------|
| 1. LED Digital Display | 18. Echo Control |
| 2. Left Equalizer | 19. Treble Volume Control |
| 3. Right Equalizer | 20. Bass Volume Control |
| 4. Power ON/OFF Switch | 21. Mic Volume Control |
| 5. USB Reader | 22. Master Volume Control |
| 6. Previous Song/Previous Station | 23. Coaxial Input Jack |
| 7. Repeat Function | 24. Optical Input Jack |
| 8. Input Selector | 25. HDMI Input |
| 9. Next Song/Next Station | 26. HDMI Output |
| 10. Menu | 27. Cooling Fan |
| 11. FM Mode: Auto scanAudio
Input Mode: Play/Pause | 28. 120V/240V Voltage Selector |
| 12. DISP. M | 29. FM Radio Antenna |
| 13. Channel Volume Control | 30. AC-3 Inputs |
| 14. IPOD/MP3 Inputs Jack | 31. DVD Input (L/R) |
| 15. Headphones Input | 32. Subwoofer Output |
| 16. Mic 1 & Mic 2 Input | 33. Speaker Output |
| 17. Delay Control | 34. AC 120V/240V Input |

Remote Control Functions

1. Mute button
2. **Input button:** Switch between input sources.
3. **Numeric key pad:** In USB mode, use to manually select tracks. In radio mode use to manually select stored stations.
4. **Scan button:** Scan between stations.
5. Spectrum display mode.
6. **Menu button:** Controls function of Master Volume (Volume, Bass, Treble, Balance)
7. **Master Volume + button:** Increases volume level.
8. **Previous button:** Move back through tracks from USB Input
9. **Play/Pause button:** Play and pause music from USB Input
10. Channel mode volume
11. **Stop button:** Stops music playing from USB input
12. **Tuning Forward button:** Move forward through radio stations.
13. **Reset button:** Resets volume to 20dB
14. **Memory button:** Allows user to save selected stations.
15. **Stereo/Mono button:** Toggles between Stereo and Mono modes.
16. **Next button:** Move forward through tracks from USB input
17. **Master Volume - button:** Decreases volume level.
18. **Repeat button:** Repeats current track from USB Input
19. **Tuning Back button:** Move back through radio stations.



WIRELESS BT STREAMING OPERATION INSTRUCTION:

External devices which have a built-in Wireless BT feature can be connected to this amplifier wirelessly to play through the amplifier's speakers. If your amp is connected to speakers, you will hear audible tones which will help for connecting.

1. Press the "INPUT" button located on the front panel and select "BT" mode.
2. Turn **ON** the Wireless BT of your external device.
3. Search for available BT devices and make sure to be within range of your amp, and wait for your device to select "PT6060CHAE" on the pairing devices lists of Wireless BT networks.
4. The unit is automatically ready to pair with your devices when you hear audible tones.
5. Now you can play music on your external device through the amplifier.

Features:

- Wireless BT Streaming Ability
- Built-in USB Playback
- VFD Display
- FM Radio
- IPOD/MP3(3.5mm) Input
- MIC/HDMI/AC-3/DVD Inputs
- BT Home Theater Amplifier
- Compact Home Theater-Stereo Receiver Style
- Built-in BT for Wireless Music Streaming
- Speaker Output
- Optical/Coaxial Digital Signal Inputs
- Multi-Channel Audio Input Selection
- MP3/WAV Audio Files Support
- Connect & Stream Audio from External Devices
- Front Panel Audio Control Center
- Radio Station Auto-Search Scan
- Spectrum Mode Functions
- Repeat Audio File Functions
- Channel Volume Adjustable
- Treble, Bass, Echo, Master & Microphone Volume Control

Wireless BT Connectivity:

- Receives Wireless Signal for Audio Streaming
- Simple & Hassle-Free Pairing Setup
- Integrated Antenna for Extended Wireless Range
- Works with All of Today's Latest Devices (Smartphones, Tablets, Laptops, Computers, etc.)
- Wireless BT Version: 5.0
- Wireless BT Network Name: 'PT6060CHAE'
- Wireless Range: 40'+ Ft.

What's in the Box:

- Desktop Stereo Amplifier
- Remote Control
- FM Antenna
- Handles

Technical Specs:

- Power Output: 2000 Watts Peak Power
- Operating Voltage: 120V/240V
- Remote Control Battery: Need 2x 'AAA' Battery (not included)
- MAX Power Output: 80 Watt x6 (@ 4 Ohm)
- RMS Power Output: 70W*3+50W*3 (@ 4 Ohm)
- Tone Control: Bass, f=100Hz +/-12dB, Treble, f=10 KHz +/-12dB
- Tone Control for Mic: Bass, f=100Hz +/-8dB, Treble, f=10 KHz +/-8dB
- Frequency Response: 20Hz-20 kHz
- Frequency Adjustment: +/-2dB
- Signal to Noise Ratio: >75 dB
- T.H.D.: <0.5%
- Radio Station Presets: Up to 40 Stations
- Separation Degree: >45dB
- Power Supply: 120V/240V, Switchable
- Dimensions (L x W x H): 16.93" x 11.81" x 4.72" -inches



WARNING:

This product can expose you to a chemical or group of chemicals, which may include "Lead (PB)" which is known in the state of California to cause cancer, birth defects, or other reproductive harm. For more info, go to <https://www.p65warnings.ca.gov/>.