

MAJORCOM IZ-2020 20 Way Intercom Central



MAJORCOM IZ-2020 20 Way Intercom Central Unit Instructions

[Home](#) » [MAJORCOM](#) » MAJORCOM IZ-2020 20 Way Intercom Central Unit Instructions 

Contents

- [1 MAJORCOM IZ-2020 20 Way Intercom Central Unit](#)
- [2 Product Information](#)
- [3 Product Usage Instructions](#)
- [4 KEY POINTS](#)
- [5 Documents / Resources](#)
 - [5.1 References](#)
- [6 Related Posts](#)

MAJORCOM:

MAJORCOM IZ-2020 20 Way Intercom Central Unit



Product Information

Specifications

- **Model:** IZ-2020
- **Audio signal:** 2.2 V
- **Speech line output:** 16
- **Bus audio signal:** -10 dBu
- **Dimensions:** 378 x 206 x 75 mm
- **Color:** Anthracite grey
- **Material:** Casing – metal
- **Weight:** 3.4 kg

Product Usage Instructions

Installation

To install the IZ-2020 20-way intercom central unit, follow these steps:

1. Choose a suitable location for the unit.
2. Connect the necessary audio and speech line outputs.
3. Ensure proper ventilation around the unit.
4. Securely mount the unit using appropriate hardware.

Operation

To operate the intercom central unit:

1. Power on the unit using the designated power source.
2. Adjust audio levels as needed using the controls provided.
3. Connect compatible devices to the unit for communication.
4. Refer to the user manual for advanced settings and troubleshooting.

Frequently Asked Questions (FAQ)

- **Q: Can I expand the number of connected devices beyond 20?**

A: The IZ-2020 is designed to support up to 20 connected devices. Exceeding this limit may impact performance.

- **Q: What should I do if the audio signal is weak?**

A: Check the audio connections and ensure that the audio levels are correctly set. If issues persist, contact customer support for assistance.

- **Q: How do I reset the unit to factory settings?**

A: Refer to the user manual for instructions on resetting the unit to factory settings. This process may vary based on the model.

IZ-2020

20-way intercom central unit

KEY POINTS

- 20-way intercom central unit
- Cascadable up to 80 directions
- Music source management
- Integrated line monitoring
- Easy installation through bus
- Music broadcasting via AUX input
- The IZ-2020 is a 20-way intercom central unit with mains power supply.
- It is possible to cascade 4 IZ-2020 to get an installation with 80 remote stations.
- The IZ-2020 is provided with monitoring system for remote lines and music broadcasting zone control.



Model	IZ-2020
Audio signal	2,2 V
Speech line output	16 Ω
Bus audio signal	- 10 dBu
Dimensions	378 x 206 x 75 mm
Color	Anthracite grey
Material	Casing : metal
Weight	3,4 kg

- www.majorcom.fr
- commercial@majorcom.fr
- +33 [0]5 61 31 86 87



[MAJORCOM IZ-2020 20 Way Intercom Central Unit](#) [pdf] Instructions
IZ-2020 20 Way Intercom Central Unit, 20 Way Intercom Central Unit, Intercom Central Unit, Central Unit

References

- [User Manual](#)

[Manuals+](#), [Privacy Policy](#)

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.