

# NETVUE NI-8100 Series Bird Feeder Camera User Guide


[Home](#) » [netvue](#) » NETVUE NI-8100 Series Bird Feeder Camera User Guide 

## Contents

- [1 NETVUE NI-8100 Series Bird Feeder Camera](#)
- [2 Product Information](#)
- [3 Product Usage Instructions](#)
- [4 FAQ \(Frequently Asked Questions\)](#)
- [5 What's In The Box](#)
- [6 Camera Structure](#)
- [7 Insert MicroSD Card](#)
- [8 Assemble Birdfy Feeder](#)
- [9 Battery Charging](#)
- [10 How To Turn On & Off The Camera](#)
- [11 Read Before Installation](#)
- [12 Setting up With the Birdfy App](#)
- [13 Installation](#)
- [14 Cleaning Birdfy Feeder](#)
- [15 How to Add Bird Seed](#)
- [16 Status Light](#)
- [17 AI Bird Recognition](#)
- [18 Documents / Resources](#)
  - [18.1 References](#)
- [19 Related Posts](#)

**netvue**

**NETVUE NI-8100 Series Bird Feeder Camera**



## Product Information

### Specifications

- Model: NI-8101/NI-8102
- FCC ID: 2AO8RNI-8101
- IC Caution: This device contains licence-exempt transmitter(s)/receiver(s) that comply with Innovation, Science and Economic Development Canada's licence-exempt RSS(s). Operation is subject

### What's In The Box

The Birdfy Feeder comes with the following items:

- Roof Dach Toit Techo Tetto Mounting Screws
- Anchors Anker Ancres Anclas Ancore
- Perch Screw Stangenschraube Vis de perche Tornillo de percha Tornillo de percha
- Birdfy Feeder
- Hose Clip Schlauchschelle Collier de serrage Abrazadera Fermaglio per tubo
- Black Strap Schwarzer Riemen Bracelet noir Correa negra Cinturino nero
- Single-sided Foam Tape Einseitiges Schaumklebeband Ruban mousse simple face Cinta de espuma de un solo lado Nastro in schiuma su un lato
- Mounting Bracket Montagehalterung Support de montage Soporte de montaje Staffa di fissaggio

### Camera Structure

The Birdfy Feeder camera consists of the following components:

- PIR Infrared Passives Infrarot Infrarouge passif Infrarrojos pasivos Infrarossi passivi
- Microphone Mikrofon
- Status Light Statuslicht Luce di stato
- Perch Barsch Perche Perca Pertica
- Lens Linse Lentille Lente Lente

- LED Infrared LED Infrarot LED Infrarouge Infrarrojos LED LED Infrarossi
- Spot Light Spot-Licht Projecteur Destacar Riflettore
- Micro SD Card Slot Micro SD-Kartensteckplatz Emplacement pour carte micro SD Ranura para tarjeta micro SD Slot per scheda micro SD
- Camera Direction Adjuster Einstellung der Kamerarichtung Regolazione della direzione della telecamera
- Antenna Antenne Antenne Antenna Antenna
- Speaker Lautsprecher Orateur Orador Altoparlante
- DC-5V

## Product Usage Instructions

### Insert MicroSD Card

1. Rotate the camera down to the bottom.
2. Open the top silicone plug.
3. Insert the MicroSD card, making sure to plug it in the right direction.
4. Finally, cover the silicone plug.

### Assemble Birdfy Feeder

Assemble the roof:

- Face up the side of the roof with the buckles.
- Align the small pillar on both the left and right side with the buckles of the white bird seed container.
- Push down to insert.
- Rotate back to install the buckle behind the white bird seed container.

## FAQ (Frequently Asked Questions)

### • How do I clean the Birdfy Feeder?

To clean the Birdfy Feeder, follow these steps:

1. Disconnect the power source.
2. Remove the roof and empty the bird seed container.
3. Wash the feeder with mild soap and water.
4. Rinse thoroughly and allow it to dry completely before reassembling.

### • How do I charge the battery?

To charge the Birdfy Feeder's battery, do the following:

1. Connect the provided charging cable to the DC-5V input on the feeder.
2. Plug the other end of the cable into a power source.
3. The status light will turn red to indicate charging and will turn green when fully charged.

### • How do I turn on/off the camera?

To turn on/off the Birdfy Feeder camera, follow these steps:

1. Locate the power button on the camera.
2. Press and hold the power button for a few seconds to turn on or off the camera.

### • How do I set up the Birdfy Feeder with the Birdfy App?

To set up the Birdfy Feeder with the Birdfy App, follow these steps:

1. Download and install the Birdfy App from the App Store or Google Play Store.
2. Open the Birdfy App and create an account.
3. Follow the on-screen instructions to connect the app to the feeder using the provided Wi-Fi credentials.
4. Once connected, you can access and control the feeder through the Birdfy App.

• **How do I add bird seed to the Birdfy Feeder?**

To add bird seed to the Birdfy Feeder, do the following:

1. Remove the roof of the feeder.
2. Pour bird seed into the white bird seed container.
3. Replace the roof securely.

## **Warning**

- **NOTE:** This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
  - Reorient or relocate the receiving antenna.
  - Increase the separation between the equipment and receiver.
  - Connect the equipment into an outlet on a circuit different from that to which thereceiver is connected.
  - Consult the dealer or an experienced radio/TV technician for help.
- The antennas used for this transmitter must be installed to provide a separation distance of at least 20 cm from all persons and must not be co-located for operating in conjunction with any other antenna or transmitter.
- FCC (USA) 15.9 prohibition against eavesdropping except for the operations of law enforcement officers conducted under lawful authority, no person shall use, either directly or indirectly, a device operated pursuant to the provision of this part for the purpose of overhearing or recording the private conversations of other unless such use is authorized by all of the parties engaging in the conversation. Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

## **IC Caution:**

This device contains licence-exempt transmitter(s)/receiver(s) that comply with Innovation, Science and Economic Development Canada's licence-exempt RSS(s). Operation is subject to the following two conditions:

- This device may not cause interference.
- This device must accept any interference, including interference that may cause undesired operation of the device.

## **What's In The Box**



Roof  
Dach  
Toit  
Techo  
Tetto




Mounting Screws  
Befestigungsschrauben  
Vis de montage  
Tornillos de montaje  
Viti di montaggio



Anchors  
Anker  
Ancres  
Anclas  
Ancore



Perch Screw  
Stangenschraube  
Vis de perche  
Tornillo de percha  
Tornillo de percha




Perch  
Barsch  
Perche  
Perca  
Pertica



Birdfy Feeder




Drilling Template  
Bohrschablone  
Gabarit de perçage  
Plantilla de perforación  
Modello di perforazione




Type C Power Cable  
Netzkabel Typ C  
Câble d'alimentation de type C  
Cable de alimentación tipo C  
Cavo di alimentazione di tipo C




Quick Guide  
Kurzanleitung  
Guide rapide  
Guía rápida  
Guida veloce




Tripod Adapter  
Stativadapter  
Adaptateur de trépied  
Adaptador de trípode  
Adattatore per treppiede




Hose Clip  
Schlauchschelle  
Collier de serrage  
Abrazadera  
Fermaglio per tubo




Black Strap  
Schwarzer Riemen  
Bracelet noir  
Correa negra  
Cinturino nero



Single-sided Foam Tape  
Einseitiges Schaumklebeband  
Ruban mousse simple face  
Cinta de espuma de un solo lado  
Nastro in schiuma su un lato




Mounting Bracket  
Montagehalterung  
Support de montage  
Soporte de montaje  
Staffa di fissaggio



Solar Panel (Purchase Separately)  
Solarpanel (Separat Erhältlich)  
Panneau solaire (à acheter séparément)  
Panel Solar (Comprar por separado)  
Pannello solare (Acquistare separatamente)





Ejector Pin  
Auswerferstift  
Broche d'éjecteur  
Perno expulsor  
Perno di espulsione



Anti-squirrel Appliance  
Anti-Eichhörnchen-Gerät  
Appareil anti-écureuil  
Aparato anti-ardilla  
Apparecchio anti-scoiattolo


## Camera Structure



## Insert MicroSD Card

Birdfy Cam comes with a built-in card slot which supports up to 128GB MicroSD card.


- **Step 1:** Rotate the camera down to the bottom.
- **Step 2:** Open the top silicone plug. Insert the MicroSD card. Make sure to plug it in the right direction.
- **Step 3:** Finally, Cover silicone plug.



## Assemble Birdfy Feeder

### Assemble the roof


- **Step 1:** Face up the side of the roof with the buckles. Align the small pillar on both the left and the right side with the buckles of the white bird seed container.
- **Step 2:** Push down to insert.
- **Step 3:** Then rotate back to install the buckle behind the white bird seed container.



### Assemble Perch


Use the provided perch screw to install the perch.





## Battery Charging


The batteries inside the camera are not fully charged according to the transportation safety regulations. Please fully charge the camera before using it. Please charge the batteries with provided Type C Port Cable (DC5V / 1.5A adapter not included). The status light will be in solid yellow when charging, and will turn to solid green when it is fully charged. It takes about 14 hours to fully charge your camera.



## How To Turn On & Off The Camera

### To turn on the camera:

Long press the power button for 3s to turn on the camera. Then the Status Light in the front of the camera will be solid blue. Double click the power button to enter WiFi mode after the prompt tone.



### To turn off the camera:

Long press the power button for 3s to turn off the camera. Then the Status Light in the front of the camera will be off.

## Read Before Installation

1. Keep Birdfy Feeder and all accessories out of reach of children and pets.
2. Make sure the camera has been fully charged (DC5V / 1.5A).
3. Working temperature: -10°C to 50°C (14°F to 122°F) Working relative humidity: 0-95%
4. Please do not expose the camera lens to direct sunlight.
5. The camera has an IP65 waterproof rating, which supports working properly under rains or snows. But it can not be soaked in water.

### Note:

1. Birdfy Feeder Cam only works with 2.4GHz Wi-Fi.
2. Strong lights may interfere with the device's ability to scan QR code.
3. Avoid placing the device behind furniture or near microwaves products. Try to keep it within range of your Wi-Fi signal.

## Setting up With the Birdfy App

Please download the Birdfy App from the App Store or Google Play and follow the in-app instructions to complete the set-up process.



## Installation


Check the following things before you drill holes on your wall:

Birdfy Feeder Cam has been successfully added to your Birdfy App and is able to stream video.

### Wall Installation:


#### • Step 1:

1. Use the provided drilling template to mark the position of holes on your wall. Use drill bit (5/16", 8mm) to drill two holes.
2. Install the anchors to fix the screws. (Install on wood skip this step.)
3. Install the Mounting Bracket on your wall with the screws provided.




- **Step 2:**

Slide the Birdfy Feeder into the bracket through the slide rail.




**Tree Installation:**

- **Step 1:** Wrap the Mounting Bracket around the tree with the Black Strap.




- **Step 2:** Slide the Birdfy Feeder into the mounting bracket.




#### Stand Installation:

- **Step 1:**
  - The Birdfy Feeder can be placed steadily on a flat surface, but for stability, we recommend that the backplane is installed and fixed on a flat surface.
  - Use the provided drilling template to mark the position of holes on flat surface. Use drill bit (5/16", 8mm) to drill two holes.




- **Step 2:**  
Install the anchors to fix the screws. (Install on wood skip this step.)




- **Step 3:**

Install the Mounting Bracket on flat surface with the screws provided.



- **Step 4:** Slide the Birdfy Feeder into the mounting bracket.




**Tripod Installation:**

Make sure you don't have the bracket installed on the bottom of the Birdfy Feeder. If you need to remove it, please take a look at "Step 2 of Cleaning Birdfy Feeder" for instructions on how to remove the bracket.


- **Step 1:**

Slide the Birdfy Feeder into the Tripod Adapter.




- **Step 2:**

Install the Birdfy Feeder on the corresponding accessories, such as a photogra-phy stand (not provided).




## Pole Installation – Hose clip

- **Step 1:** Attach Birdfy Feeder to the pole with the Hose Clip turning the handle clockwise.




- **Step 2:** Slide the Birdfy Feeder into the bracket through the slide rail.




- **Step 3:** Tighten the hose clips by turning the handles clockwise. Attach the mounting arm to the back of the solar panel by screwing it in.


Solar Panel (Purchase Separately)  
Solarpanel (Separat Erhältlich)  
Panneau solaire (à acheter séparément)  
Panel Solar (Comprar por separado)  
Pannello solare (Acquistare separatamente)



- **Step 4:** Wrap Single-sided Foam Tape around the pole. Then wrap the Anti-squirrel Appliance around the pole, and finally snap the concealed buckle.




- **Step 5:** Birdfy Feeder is installed and ready for bird watching.




## Cleaning Birdfy Feeder

- **Step 1:** Unplug the charging cable and put on the silicone cover.




- **Step 2:** Using the Pull Tab on the base of the feeder, remove the Birdfy Feeder from the bracket.







Pull Tab  
Lasche ziehen  
Tirette  
Lengüeta de arrastre  
Tirare la linguetta

or




Pull Tab  
Lasche ziehen  
Tirette  
Lengüeta de arrastre  
Tirare la linguetta


- **Step 3:** Open up the buckle on the back of the Birdfy Feeder, and pull up on the roof to open.




- **Step 4:** Pour water into the top of the seed reservoir. Do not wash the camera or any of its components. They are water resistant, not water-proof.  
Dry the feeder, including the seed reservoir.




- **Step 5:** Re-attach the Roof: Push the roof down and engage the snaps on the back of the Birdfy Feeder.



- **Step 6:** Re-attach the bracket to the Birdfy Feeder base. Adjust the angle for both the Birdfy Feeder and camera.




- **Step 7:** Open the silicone plug, re-plug in the Solar Panel.




## How to Add Bird Seed

- **Step 1:** Open up the buckle on the back of the Birdfy Feeder, and pull up on the roof to open.



- **Step 2:** You can add bird seed. Finally, close the roof back.



## Status Light

This camera uses status light to communicate.

- **Solid Blue** Working
- **None** Sleep/Power Off
- **Solid Yellow** Charging
- **Solid Green** Charging Finished

## AI Bird Recognition


- **AI version:** The service is free for life.
- **Lite version:** This service requires a subscription.

AI Bird Recognition has undergone massive machine learning and uses AI intelligent recognition algorithms to inform you in real time “what species of bird are coming”, automatically save the bird images/videos data for you, and also provide bird knowledge learning and so on.

Contact us at:

- [support@birdfy.com](mailto:support@birdfy.com)
- 1(886)749-0567
- Mon-Fri, 9am-5pm, PST
- [www.birdfy.com](http://www.birdfy.com)

Documents / Resources

	<p><a href="#">NETVUE NI-8100 Series Bird Feeder Camera</a> [pdf] User Guide</p> <p>NI-8100 Series Bird Feeder Camera, NI-8100 Series, Bird Feeder Camera, Feeder Camera, Camera</p>
-----------------------------------------------------------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

References

- [🏠 Birdfy Official Site - Birds in Sight, Joy in Mind](#)
- [User Manual](#)