



NIGHTSTICK XPR-5584 Integritas Intrinsically Safe Rechargeable Lantern with Magnetic Base Instruction Manual

[Home](#) » [NIGHTSTICK](#) » NIGHTSTICK XPR-5584 Integritas Intrinsically Safe Rechargeable Lantern with Magnetic Base Instruction Manual 

Contents

- [1 NIGHTSTICK XPR-5584 Integritas Intrinsically Safe Rechargeable Lantern with Magnetic Base](#)
- [2 WARNINGS – INTRINSICALLY SAFE](#)
- [3 INITIAL USE](#)
- [4 DAILY USE](#)
- [5 REPLACING LITHIUM-ION RECHARGEABLE BATTERY](#)
- [6 OPERATION](#)
- [7 WARRANTY](#)
- [8 Documents / Resources](#)
- [9 Related Posts](#)



NIGHTSTICK XPR-5584 Integritas Intrinsically Safe Rechargeable Lantern with Magnetic Base



WARNINGS – INTRINSICALLY SAFE

- Warning: To prevent ignition of a hazardous atmosphere, do not locate the charger for this product in the hazardous environment. The charger for this product must be located in an area known to be non-hazardous ONLY.
- Warning: To prevent ignition of a hazardous atmosphere, do not attempt to charge this product in the hazardous environment. This task must ONLY be
- performed in an area known to be non-hazardous
- Warning: Lithium-ion batteries must be used and charged properly. Improper use can result in serious injury, fire, or death.
- Warning: Use only the included and approved 5584-BATT rechargeable battery pack from Bayco Products.
- Warning: Do NOT attempt to use any other rechargeable or non-rechargeable batteries with this light.
- Warning: To prevent ignition of a hazardous atmosphere, do not open or remove the bottom plate and/or lens bezel in a hazardous environment. This task
- must ONLY be performed in an area known to be non-hazardous.
- Warning: When exchanging the rechargeable battery pack, use only the approved 5584-BATT rechargeable battery pack from Bayco Products.
- Warning: To prevent ignition of a hazardous atmosphere, the rechargeable battery pack must only be exchanged in an area known to be non-hazardous.
- Warning: Do not expose the rechargeable battery pack to water or salt water, or allow the battery pack to get wet.
- Warning: Do not store the rechargeable battery pack with metallic objects that may cause a short circuit.
- Warning: Substitution of components may impair intrinsic safety.

SPECIAL INSTRUCTIONS FOR INTRINSIC SAFETY

For personal safety, always confirm the rating of any known hazardous or potentially hazardous location where the light is to be used.

INITIAL USE

Warning: To prevent ignition of a hazardous atmosphere, do not attempt to charge this product in the hazardous

environment. This task must ONLY be performed in an area known to be non-hazardous.

Fully charge the XPR-5584 before the first use, or if the battery is new or has been unused for several months. The maximum charge time required is approximately 6 hours.

DAILY USE

WARNING: TO PREVENT IGNITION OF A HAZARDOUS ATMOSPHERE, DO NOT ATTEMPT TO CHARGE THIS PRODUCT IN THE HAZARDOUS ENVIRONMENT. THIS TASK MUST ONLY BE PERFORMED IN AN AREA KNOWN TO BE NON-HAZARDOUS.

- Use only the supplied Nightstick charger, 5584-BATT rechargeable battery pack and AC or DC adapter. For best performance, charge the 5584 when the flashlight beam starts to dim.
- Connect the AC power adapter to the charger. The LED indicator will not be illuminated at this point.
- With the flashlight facing forward, slide the 5584 into the charger until the contacts snap into place.
- The LED indicator changes to constant red indicating the 5584 is properly inserted into the charger and is charging. The LED indicator remains red until the battery is fully charged. At full charge, the LED indicator turns green.
- The total time to fully charge the 5584 varies depending on the remaining charge in the battery pack.
- To confirm a full charge, keep the 5584 in the charger and turn it on. The LED indicator will change to red. Turn off the 5584. If the 5584 is fully charged, the LED indicator will turn green. If not, it remains red until the charge is completed and the LED indicator turns green. The 5584 will now be fully charged.

REPLACING LITHIUM-ION RECHARGEABLE BATTERY

The XPR-5584 is designed to allow the end user to replace the battery pack if necessary. Carefully follow the instructions below:

CHARGER INPUT: 12 VDC MAX.

WARNING: WHEN EXCHANGING THE RECHARGEABLE BATTERY PACK, USE ONLY THE APPROVED 5584-BATT RECHARGEABLE BATTERY PACK FROM BAYCO PRODUCTS.

WARNING: TO PREVENT IGNITION OF A HAZARDOUS ATMOSPHERE, THE RECHARGEABLE BATTERY PACK MUST ONLY BE EXCHANGED IN AN AREA KNOWN TO BE NON-HAZARDOUS.

- Loosen the screws located on the bottom of the light and remove the plate to expose the battery pack.
- The battery is connected to the light with a wire that has a snap connector. Remove the battery pack from the light by first disconnecting the wires that snap together.
- Using only the approved replacement 5584-BATT rechargeable battery pack from Bayco Products, place the new battery pack into the housing and reconnect the wires.
- Replace the base plate and tighten all the screws. **CAUTION:** Do NOT overtighten the screws. Doing so may damage the threads and impact the light's intrinsic safety.

OPERATION

Turn Light On/Off:

Press and release the flashlight switch. The light will turn on in high brightness mode. Press and release to turn off.

Select Brightness Level:

Press and hold the flashlight switch. The light will cycle from high to low and back at a rate of approximately one mode per second and will continue to cycle while the switch is held down. Release the switch when the desired

brightness level is reached.

Rear Light:

The rear green LED light stays on while flashlight is in operation regardless of mode selected.

WARRANTY

LIMITED LIFETIME WARRANTY


Bayco Products, Inc. warrants this product to be free from defects in workmanship and materials for the original purchaser’s lifetime. The Limited Lifetime Warranty includes the LEDs, housing and lenses. Rechargeable batteries, chargers, switches, electronics and included accessories are warranted for a period of two years with proof of purchase. Normal wear and failures which are caused by accidents, misuse, abuse, faulty installation and lightning damage are excluded.

We will repair or replace this product should we determine it to be defective. This is the only warranty, expressed or implied, including any warranty of merchantability or fitness for a particular purpose.

For a complete copy of the warranty, go to www.baycoproducts.com/bayco-product-support/warranties. Retain your receipt for proof of purchase.

Mode D’emploi
XPR-5584

Documents / Resources

	<p>NIGHTSTICK XPR-5584 Integritas Intrinsically Safe Rechargeable Lantern with Magnetic Base [pdf] Instruction Manual</p> <p>XPR-5584, Integritas Intrinsically Safe Rechargeable Lantern with Magnetic Base, XPR-5584 Integritas Intrinsically Safe Rechargeable Lantern with Magnetic Base, Safe Rechargeable Lantern with Magnetic Base, Lantern with Magnetic Base, Safe Rechargeable Lantern, Rechargeable Lantern, Lantern</p>
------------------------------------------------------------------------------------	------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------