



OCOM OCPP-M06 Bluetooth Android Printer Thermal Instructions

[Home](#) » [ocom](#) » OCOM OCPP-M06 Bluetooth Android Printer Thermal Instructions 



OCPP- M06 OCOM bluetooth android printer thermal
(Model Number: OCPP- M06)

Contents

- [1 OCPP-M06 Bluetooth Android Printer Thermal](#)
- [2 Specification:](#)
- [3 Relevant documents:](#)
- [4 Documents / Resources](#)
 - [4.1 References](#)
- [5 Related Posts](#)

OCPP-M06 Bluetooth Android Printer Thermal

This mini printer OCPP-M06 is a Android (or IOS+ Android) ,Window, Linux, JAVA compatible battery powered 58mm portable mobile thermal pos printer which combines USB,RS232 Serial and Bluetooth (optional) communication ways together. This printer could be powered by rechargeable battery, power adapter, or car charger (depending on specified models) . Special model can connect with 8 smart devices for printing at same time. We have CE, FCC and other required certifications.

Specification:

Overall Dimension (WxDxH)		105x75x45mm
Weight		134g
Color		Black
Print method		Thermal line printing
Print commands		ESC/POS compatible command set
Effective print width		48mm
Print speed		Up to 90mm/sec
Resolution		8 dots/mm(203dpi)
Print font		12×24/ 24×24
Column capacity		32 columns/ 16columns
Character size		1.5 x 3.0 mm(W x H)/ 3.0×3.0mm(WxH)
Paper dimensions		58.0±0.1mm x diameter 40.0mm
Paper thickness		0.06 to 0.08mm
Character set		Alphanumeric/ Chinese Kanji
Interface		USB, RS-232□Bluetooth (optional)
Flash		256KB
Power Adapter		9V DC/2A
Battery Power		7.4V DC/ 1500mAh; battery can stay by for 4-5 days, when it is full power, it can print 120-150m paper
Other features		Paper detection, manual shut down
Working conditions		Temperature:-10-50 degC, Humidity:10%□90%
Storage conditions		Temperature:-20-70 degC, Humidity:5%□95%
Device name		Can be customized, letter and digital for option, at max 30 ASCII characters.
Password		Enter default pairing code "1234", it can be customized or change by customer itself. At max 6 digitals.
Power plug dimension		3.5*1.1mm
Ordering Info.	OCPP-M06-BB	Android, USB+COM+Bluetooth, Battery.
	OCPP-M06-BB-AI	Android+IOS, USB+COM+Bluetooth, Battery.
	OCPP-M06-B	Android, USB+COM+Bluetooth, without Battery;
	OCPP-M06-U	Mini printer, Android, USB+COM, without Battery.
	r1rPP-MAR-RR-A A	Anrlrnrl4-lflc l lcR4-rY1M4-Rlturstnnth Rattnnt 7 am-lt-nit-l 4-1 annin ripvirra c cunnnr-trarl

Application Area:

Compared to the traditional thermal receipt printer, mini printer has smaller body, more reliable capability, more steady printing and portable advantages. The Mini printer can work on a lot of locations, such as the TAXI bill printing, administrative fees receipt printing, post receipt printing, restaurant ordering information printing, online payment information printing, etc. With the rapid popularity of smartmobile, tablet and so on, Mini printer will be more widely used in the near future.

Key words: thermal printer, bluetooth printer, mini printer, portable printer, pos printer, mobile printer, receipt printer, wireless printer, ticket printer, bill printer, qr code printer, pocket printer, invoice printer, mini printer, 58mm bluetooth printer, 2inch bluetooth printer.

Relevant documents:

- [Specification](#)
- [Program Manual](#)
- [Instruction Manual](#)
- [Driver for WinXP Win2000 WinVista Win8-32bit](#)
- [Driver for Win8-64bit](#)
- [Driver for Linux](#)
- [Printer Parameters Setting Tools](#)
- [USB Printdemo\(Application Software demo\)](#)
- [Bluetooth Printdemo\(Application Software demo\)](#)
- [SDK for Android](#)
- [CD Files](#)



Documents / Resources

	OCOM OCPP-M06 Bluetooth Android Printer Thermal [pdf] Instructions OCPP-M06 Bluetooth Android Printer Thermal, OCPP-M06, Bluetooth Android Printer Thermal, Android Printer Thermal, Printer Thermal, Thermal
---	--

References

- ocominc.com/download/14050516464735.html
- ocominc.com/file_download/156.html
- ocominc.com/file_download/157.html
- ocominc.com/file_download/158.html

- ocominc.com/file_download/159.html
- ocominc.com/file_download/160.html
- ocominc.com/file_download/162.html
- [User Manual](#)