

Signalyst Z1 Plus HQPlayer NAA



Signalyst Z1 Plus HQPlayer NAA User Guide

[Home](#) » [Signalyst](#) » Signalyst Z1 Plus HQPlayer NAA User Guide 

Contents

- [1 Signalyst Z1 Plus HQPlayer NAA](#)
- [2 Specifications](#)
- [3 Product Usage Instructions](#)
- [4 FAQ](#)
- [5 How to use HQPlayer NAA for Z1 Plus](#)
- [6 Before using HQ Player NAA](#)
- [7 Reference](#)
- [8 Documents / Resources](#)
 - [8.1 References](#)



Signalyst Z1 Plus HQPlayer NAA



Specifications

- **Required:** HQ Player 5 Desktop on the computer, VitOS Manager app on a mobile device
- **Connection:** Z1 Plus, computer, and mobile device need to be on the same network
- **Output:** Connect Z1 Plus to USB DAC

Product Usage Instructions

Step 1: Setting up HQPlayer NAA on Z1 Plus

1. Power on Z1 Plus and use VitOS Manager on a mobile device to discover Z1 Plus.
2. Check HQPlayer NAA status in Applications section. If Not Installed, install HQPlayer NAA.
3. Install HQPlayer NAA and wait for it to start running.
4. Ensure Z1 Plus is not playing music in other apps for HQPlayer 5 Desktop to find HQPlayer NAA.

Step 2: Controlling Z1 Plus with HQPlayer 5 Desktop

1. Download the HQPlayer 5 Desktop application from [here](#).
2. Open HQPlayer 5 Desktop and go to File > Settings to open the Settings Page.
3. Select NetworkAudioAdapter in the Backend option under the Outputs interface.
4. Select the Z1 Plus device from the Device Option and click OK.
5. Browse and select the music content folder, then choose the music to start playing.
6. Open VitOS Manager to see HQPlayer NAA displayed as an audio source, indicating playback from Z1 Plus.
7. (Optional) Use the hip control app on a mobile phone to control the playback of HQPlayer.

FAQ

- **Q:** What should I do if I can't find Z1 Plus in VitOS Manager?
- **A:** Ensure Z1 Plus is powered on and connected to the same network as your computer and mobile device. Restart VitOS Manager and try again.
- **Q:** How can I stop playback in HQPlayer NAA on Z1 Plus?

- **A:** In HQPlayer NAA, click the Stop playing Button. When the button color turns gray, playback has stopped.
- **Q:** Can I use other DACs with Z1 Plus?
- **A:** Z1 Plus is designed to work with USB DACs. Ensure your DAC is compatible with Z1 Plus for optimal performance.

How to use HQPlayer NAA for Z1 Plus



Before using HQ Player NAA

1. Please make sure that your computer has HQ Player 5 Desktop installed
2. Ensure that your mobile device has the latest version of the VitOS Manager application installed
3. And your computer, mobile device, and Z1 Plus need to be connected to the same network.
4. Make sure your Z1 Plus is connected to a USB DAC.

Step 1: Use Vitos Manager to control Z1 Plus, install HQPlayer NAA in Z1 Plus


1. Power on the Z1 Plus and use the Vitos Manager app on your mobile device to discover the Z1 Plus. Below is a screenshot of vitos manager discovery Z1 Plus page.




After finding the Z1 Plus, click "Manage" to enter the main page of the Z1 Plus.

Language English

1.2



In the Applications section of the home page, check the status of the HQPlayer NAA. If the status is "Not Installed", you need to install HQPlayer NAA for this Z1 Plus. Click ">" to enter the HQPlayer NAA page.





Click "Install" to install HQPlayer NAA to this Z1 Plus.


HQPlayer NAA (Network Audio Adaptor) makes it possible for a VitOS device to act as a network adaptor for a HQPlayer, which is running on a PC or a music server. With this scenario, music data processing is performed by the HQPlayer and the processed data is then asynchronously streamed over network to the NAA interfacing to the DAC. With this asynchronous audio data transfer provides good isolation between audio processing and audio playback.

[\[Learn More \]](#)

2. wait for the installation to complete, and the status of HQPlayer NAA will be displayed as "Running", indicating that HQPlayer NAA has been started and running. The screenshot below shows the HQPlayer NAA page and home page.




3. in order for HQPlayer 5 Desktop on the computer to find the HQPlayer NAA of Z1 Plus, please make sure that Z1 Plus is not playing music in other apps. If the color of the "Stop play" Button on the HQPlayer NAA page is orange, it means that Z1 Plus is playing music in other apps, then you need to click the "Stop playing" Button. The color of the "Stop playing" Button is gray to indicate that the music has been stopped.




Step 2: Use the computer's HQPlayer 5 Desktop application to control Z1 Plus to play music


1. HQPlayer 5 Desktop application download link: <https://www.signalyst.com/consumer.html> Select the version corresponding to your computer to download




2. Open the HQPlayer 5 Desktop application on the computer




3. Select “File” In the upper left corner, and then click “Settings...” To open the “Settings” Page




4. On the “Settings” page, find the “Backend” option in the “Outputs” interface and select “NetworkAudioAdapter”.




- After selecting "Networkaudioadapter" In the "Backend" Option, the "Device" Option will automatically find the Z1 Plus device that can be connected. After selecting the Z1 Plus device, click "OK" To set it to take effect.




- Click the "Browse..." Button to open the selected music content folder.



7. Select the folder where you save the music, and then click the “Select folder” Button.




8. After importing the music file, select the music to start playing.



9. Install and open Vitos Manager, “HQPlayer NAA” Will be displayed in the audio source on the home page, indicating that Z1 Plus is playing songs from HQPlayer NAA.





10. Click the button marked above. When the background color of the button is dark gray (as shown in the figure below), it means that the hqpdcontrol app on the mobile phone can control the playback of hqplayer. (Note: If you do not use the mobile app to play, you can ignore this step)




Reference

- Diagram of the connection of HQPlayer NAA and Z1 Plus





Documents / Resources

	<p>Signalyst Z1 Plus HQPlayer NAA [pdf] User Guide Z1 Plus, Z1 Plus HQPlayer NAA, HQPlayer NAA, NAA</p>
---	--

References

- [Signalyst](#)
- [User Manual](#)

[Manuals+](#), [Privacy Policy](#)

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.