



# SUNCO LED Ceiling Panel Installation Guide

[Home](#) » [SUNCO](#) » SUNCO LED Ceiling Panel Installation Guide 

## Contents

### [1 SUNCO LED CEILING PANEL 40W Install Guide and Manual](#)

- [1.1 EASY INSTALLATION RECESSED](#)
- [1.2 WARNING](#)
- [1.3 WIRING DIAGRAM](#)
- [1.4 EASY INSTALLATION SUSPENSION](#)
- [1.5 WARNING](#)
- [1.6 SPECIFICATIONS](#)

### [2 Documents / Resources](#)

### [3 Related Posts](#)

## SUNCO LED CEILING PANEL 40W Install Guide and Manual



### EASY INSTALLATION RECESSED

**Required Tools:** Drill, Ladder, Hammer, Pliers, Tape Measure, Pencil, Philips Screwdriver.


Prior to install, remove the existing light fixture (if any) from the ceiling.

1. **Turn off the switch and circuit breaker before installing this LED light fixture.**

**2. Turn the Ceiling Panel face down on a flat surface.**


- Unscrew the (2) driver covers and set aside the screws.

**3. Pop out (2) knockouts (choice of 6).**




**4. Connect conduit to each knockout.**

- Pass wires through.




**5. Connect the supply wires to the Ceiling Panel wires with included wire nuts.**

- Black to Black (live);
- White to White (neutral);
- Green to Green (ground).




**6. (Optional) If using a dimmer (not included), connect DIM+ and DIM- wiring of Ceiling Panel to your dimmer with included wire nuts.**




**7. Replace driver covers.**


- Tighten the screws.



**8. Locate the (2) protective brackets on back of panel. Bend up 90°.**




9. **Twist 90° so hook faces outside edge of Ceiling Panel.**



10. **Install LED Ceiling Panel light in ceiling, using protective brackets.**

11. **Turn on circuit breaker and test the light.**




## WARNING

To reduce the risk of fire, electric shock or injury to people:

- Installation should be performed by a professional, qualified electrician familiar with the construction and operation of this product and the hazards involved.
- Abide by related regional and local laws or regulations.
- Proper grounding is required to ensure safety.
- Not suitable for a wet environment.
- LED must be installed in an appropriate environment to work. Harsh environments may shorten the life or damage the light.
- Check for damage during shipping prior to install. If the product is damaged, do not use it.
- Turn off the switch and circuit breaker before installing this LED light fixture. Accurately verifying no voltage on the lines with an appropriate meter is recommended prior to install.
- After verifying no voltage, disconnect wires and remove existing light fixture from ceiling (if any).
- To ensure efficient light, regularly clean the light panel. Don't clean with harsh solvents; use a dry cloth.
- Use safety precautions. Safety eyeglasses and gloves are recommended.

## WIRING DIAGRAM




To make the light panel dimmable, connect a compatible dimmer (not included) to the dimming signal wires of the luminaire. Suitable for Constant Current Reduction Dimming 0-10V.

## EASY INSTALLATION SUSPENSION


**Required Tools:** Drill, Ladder, Hammer, Pliers, Tape Measure, Pencil, Philips Screwdriver.

**NOTE:** 2 piece suspension kits (not included) required for suspension install.


1. **Turn off the switch and circuit breaker before installing this LED light fixture.**
2. **Turn the Ceiling Panel face down on a flat surface.**
  - Unscrew the (2) driver covers and set aside the screws.
3. **Pop out (2) knockouts** (choice of 6).




4. **Connect conduit to each knockout.**
  - Pass wires through.



5. **Connect the supply wires to the Ceiling Panel wires with included wire nuts.**
  - Black to Black (live);
  - White to White (neutral);
  - Green to Green (ground).




6. (Optional) **If using a dimmer (not included), connect DIM+ and DIM- wiring of Ceiling Panel to your dimmer with included wire nuts.**




7. **Replace driver covers.**

- Tighten the screws.




8. **Drill (2) holes in the ceiling. Place the anchors into hole. Insert the wire rope and screw.**

- Refer to install manual of your suspension kit for complete details.




9. **Adjust the support rope/wire so Ceiling Panel hangs horizontally.**

- Suspension kit is not included.



10. **Install LED Ceiling Panel light in ceiling, using protective brackets.**

11. **Turn on circuit breaker and test the light.**



**WARNING**


To reduce the risk of fire, electric shock or injury to people:

- Installation should be performed by a professional, qualified electrician familiar with the construction and operation of this product and the hazards involved.
- Abide by related regional and local laws or regulations.
- Proper grounding is required to ensure safety.
- Not suitable for a wet environment.
- LED must be installed in an appropriate environment to work. Harsh environments may shorten the life or damage the light.
- Check for damage during shipping prior to install. If the product is damaged, do not use it.
- Turn off the switch and circuit breaker before installing this LED light fixture. Accurately verifying no voltage on the lines with an appropriate meter is recommended prior to install.
- After verifying no voltage, disconnect wires and remove existing light fixture from ceiling (if any).
- To ensure efficient light, regularly clean the light panel. Don't clean with harsh solvents; use a dry cloth.
- Use safety precautions. Safety eyeglasses and gloves are recommended.

## SPECIFICATIONS

Voltage	100-277V
Wattage	40W
Suitable for Locations Ingress	Damp
Housing	SPCC+PS lens
Weight	4.85 lbs
Warranty	10 years

## Documents / Resources

	<a href="#">SUNCO LED Ceiling Panel</a> [pdf] Installation Guide LED Ceiling Panel, 40W LED Ceiling Panel
---	--