



# Superlux LLED1-SC101 Smart Control Switch Installation Guide

## Contents [ [hide](#) ]

- [1 Superlux LLED1-SC101 Smart Control Switch](#)
- [2 Installation Instructions](#)
- [3 Documents / Resources](#)
  - [3.1 References](#)
- [4 Related Posts](#)



## Superlux LLED1-SC101 Smart Control Switch



## Installation Instructions

**Model:** LLED1-SC101

Smart Control switch (input 5V to 24V ELV, Output 12V) IP67

- Will turn lights on/off, dim and pre-set on and off times via remote Smart Life app
- It is recommended that this unit is installed by a registered electrician.
- Isolate the electrical supply
- Use a Constant voltage, 12Volt DC driver (5V-24V)
- Choose a Driver supply with a wattage that exceeds the total wattage of all fixtures used in aggregate on your circuit. The switch has a maximum capacity of 96Watts.

Place switch after the Driver and before the first Light. When pushing connectors together, first check the orientation of the Key and Slot to ensure correct alignment of polarity. Then twist cap onto thread to secure and ensure water tightness.

- Ensure that the extra low voltage connections are watertight so that the fixture cables do not siphon water. Install switch in a dry location away from where water may pool.
  - Setting up your wireless connection to the Smart Life App
    - Will turn lights on/off, dim and pre-set on and off times once
1. Install the Tuya “Smart Life app” use this QR code for the link to download the application or search manually in the apple store or play store apps on your device.



2. Open and log in (create login if new)
  3. Tap “add device” then add Manually
  4. Select “Lighting” on the left hand side
  5. Scroll down and select “strip light (Wifi)”
  6. Hold the button down on the LLED1-SC101 smart switch for 10 seconds until connected lights flash rapidly
  7. Follow instructions from application to connect to your Wifi network you will need to enter your Wifi network password.
  8. This should allow you to pair the switch to the application for remote switching,
- if this did not work please see further information for trouble shooting on this web page:

<https://developer.tuya.com/en/docs/iot/tuya-smart-app-smart-lifeappadvantages? id=K989r qa49rluq>

Please Keep instructions with owner for future reference

## Documents / Resources

	<p><a href="#">Superlux LLED1-SC101 Smart Control Switch</a> [pdf] Installation Guide  LLED1-SC101 Smart Control Switch, LLED1-SC101, LLED1-SC101 Switch, Smart Control Switch, C  ontrol Switch, Smart Switch, Switch</p>
--	--

## References

- [Tuya IoT Development Platform](#)

Contents [ [hide](#)

- [1 Superlux LLED1-SC101 Smart Control Switch](#)
- [2 Installation Instructions](#)
- [3 Documents / Resources](#)
  - [3.1 References](#)
- [4 Related Posts](#)



## Superlux LLED1-SC101 Smart Control Switch



### Installation Instructions

**Model:** LLED1-SC101

Smart Control switch (input 5V to 24V ELV, Output 12V) IP67

- Will turn lights on/off, dim and pre-set on and off times via remote Smart Life app
- It is recommended that this unit is installed by a registered electrician.
- Isolate the electrical supply
- Use a Constant voltage, 12Volt DC driver (5V-24V)
- Choose a Driver supply with a wattage that exceeds the total wattage of all fixtures used in aggregate on your circuit. The switch has a maximum capacity of 96Watts.

Place switch after the Driver and before the first Light. When pushing connectors together, first check the orientation of the Key and Slot to ensure correct alignment of polarity. Then twist cap onto thread to secure and

ensure water tightness.

- Ensure that the extra low voltage connections are watertight so that the fixture cables do not siphon water.  
Install switch in a dry location away from where water may pool.
- Setting up your wireless connection to the Smart Life App
  - Will turn lights on/off, dim and pre-set on and off times once

1. Install the Tuya “Smart Life app” use this QR code for the link to download the application or search manually in the apple store or play store apps on your device.




2. Open and log in (create login if new)
3. Tap “add device” then add Manually
4. Select “Lighting” on the left hand side
5. Scroll down and select “strip light (Wifi)”
6. Hold the button down on the LLED1-SC101 smart switch for 10 seconds until connected lights flash rapidly
7. Follow instructions from application to connect to your Wifi network you will need to enter your Wifi network password.
8. This should allow you to pair the switch to the application for remote switching,  
if this did not work please see further information for trouble shooting on this web page:

<https://developer.tuya.com/en/docs/iot/tuya-smart-app-smart-lifeappadvantages? id=K989r qa49rluq>

Please Keep instructions with owner for future reference

## Documents / Resources

	<p><a href="#">Superlux LLED1-SC101 Smart Control Switch</a> [pdf] Installation Guide LLED1-SC101 Smart Control Switch, LLED1-SC101, LLED1-SC101 Switch, Smart Control Switch, Control Switch, Smart Switch, Switch</p>
---	---

## References

-  [Tuya IoT Development Platform](#)