



## Z Wave ZW075-C16 Smart Switch Gen5 Z-Wave Protocol Implementation Conformance Statement Instructions

[Home](#) » [Z-Wave](#) » Z Wave ZW075-C16 Smart Switch Gen5 Z-Wave Protocol Implementation Conformance Statement Instructions 



Smart Switch Gen5



### Z-Wave Protocol Implementation Conformance Statement

#### Contents

- [1 General Information](#)
- [2 Z-Wave Product Information](#)
- [3 Z-Wave Technical Information](#)
- [4 Association Group Information](#)
- [5 Controlled Command Classes \(4\):](#)
- [6 Documents / Resources](#)
- [7 Related Posts](#)

## General Information

Product Identifier:	ZW075-C16
Brand Name:	Aeotec
Product Version:	HW: 75 FW: 3.26
Z-Wave Certification #:	ZC10-14090009

## Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

## Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x004B
Z-Wave Product Type:	0x0003
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.00
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

## Association Group Information

Group # / Max Nodes	Description
1 / 5	Group 1 is assigned to the Lifeline association group and every device has 5 nodes to associate. When the switch is turned on or off using the action button, the switch will send a basic report of its status to the nodes in association group 1. To change what kind of signal is sent to the nodes in group 1, please see the detailed description of configuration parameter 80.
2 / 5	When the product receives a controlling Basic Set CC/Switch Binary Set CC/ Scene Activation Set CC, which will cause the product's load state to be changed, which will lead to send the Basic Set CC/Switch Binary Set CC /Scene Activation Set CC to nodes in group 2.


## Controlled Command Classes (4):

Basic	Hail
Scene Activation	Switch Binary

Copyright © 2012-2021 Z-Wave Alliance. All Rights Reserved. All Logos property of respective rights' holders, no claim intended.

Generated @ August 20, 2021

## Documents / Resources

 Z-Wave Plus Smart Switch Gen5	<a href="#">Z Wave ZW075-C16 Smart Switch Gen5 Z-Wave Protocol Implementation Conformance Statement</a> [pdf] Instructions ZW075-C16 Smart Switch Gen5, ZW075-C16, Smart Switch Gen5, Z-Wave Protocol Implementation Conformance Statement
---	---

[Manuals+](#)