

## Logitech 961-000489-cr

# Logitech Circle View Weatherproof Wired Home Security Camera User Manual

Model: 961-000489-cr

## 1. INTRODUCTION

Thank you for choosing the Logitech Circle View Weatherproof Wired Home Security Camera. This manual provides essential information for the proper installation, operation, and maintenance of your device. The Circle View camera is designed to integrate seamlessly with Apple HomeKit Secure Video, offering advanced security features and high-quality video surveillance for your home.

## 2. PRODUCT OVERVIEW

### 2.1 Key Features

- **Logitech TrueView Video:** Experience 1080p HD video with a 180° wide-angle field of view, capturing details clearly.
- **Enhanced Night Vision:** Infrared-powered night vision provides clear visibility up to 15 feet in low-light conditions.
- **Weatherproof Design:** The IP64-rated body ensures durability and protection against dust and water, suitable for various environments.
- **Privacy Features:** Tilt the camera down or use the rear on/off button for immediate privacy.
- **Apple HomeKit Secure Video:** Designed exclusively for Apple HomeKit, offering end-to-end encryption and in-home video analysis.
- **Two-Way Audio:** Communicate through the camera with built-in microphone and speaker.

### 2.2 Camera Components

The following diagram illustrates the main components of your Logitech Circle View camera:



- 1. LED de estado de grabación
- 2. Cuerpo resistente al polvo y al agua
- 3. HD 1080p con diagonal de 180°
- 4. Funciona con Apple HomeKit

- 5. Inclínación de privacidad pivotante
- 6. Cable de alimentación de 6 m
- 7. Base de metal resistente
- 8. Botón de cambio fácil

**Image Description:** A detailed diagram of the Logitech Circle View camera, highlighting its key parts. Labels indicate: 1. Recording Status LED, 2. Dust and Water Resistant Body, 3. 180° Diagonal 1080p HD Lens, 4. 'Works with Apple HomeKit' indicator, 5. Pivoting Privacy Tilt mechanism, 6. 6m Power Cable, 7. Durable Metal Base, and 8. Easy Toggle On/Off Button.



**Image Description:** A front-facing view of the Logitech Circle View camera, showcasing its sleek, dark gray design with the lens and a red status indicator light visible.

### 3. SETUP INSTRUCTIONS

---

Follow these steps to set up your Logitech Circle View camera:

#### 3.1 Unboxing and Placement

1. Carefully remove all components from the packaging.
2. Choose a suitable location for your camera. Consider the 180° field of view and ensure adequate Wi-Fi signal strength.
3. For outdoor use, ensure the camera is positioned to take advantage of its IP64 weatherproof rating.



## CUERPO RESISTENTE A LA INTEMPERIE

**Image Description:** The Logitech Circle View camera is shown mounted on an exterior wall, with raindrops visible, demonstrating its weatherproof capability.

### 3.2 Power Connection


Connect the included power cable to the camera and plug it into a power outlet. The camera requires a continuous power supply to operate.

### 3.3 Apple HomeKit Integration

The Logitech Circle View camera is designed exclusively for Apple HomeKit. You will need an iOS device (iPhone, iPad) and a HomeKit home hub (Apple TV, HomePod, or iPad set as a home hub) to use the camera.

1. Open the **Home app** on your iOS device.
2. Tap the **Add Accessory (+)** button.
3. Scan the HomeKit setup code located on the camera or its packaging.
4. Follow the on-screen prompts to add the camera to your HomeKit setup, assign it to a room, and configure recording options.





## COMPATIBLE CON APPLE HOMEKIT SECURE VIDEO

(requiere dispositivo iOS compatible, plan iCloud y home hub)

**Image Description:** A setup showing the Logitech Circle View camera alongside an Apple HomePod and an iPhone displaying the Apple Home app interface with live camera feed, illustrating its compatibility with Apple HomeKit Secure Video.

### 3.4 Mounting (Optional)

The camera includes a wall-mounting bracket for secure installation. Use appropriate screws and anchors for your wall type. Ensure the camera is securely fastened and the power cable is routed safely.

## 4. OPERATING INSTRUCTIONS

### 4.1 Live Viewing and Recording

Access your camera's live feed and recorded events through the Apple Home app on your iOS devices. HomeKit Secure Video allows for intelligent detection of people, animals, and vehicles, with recordings stored securely in iCloud.

### 4.2 Two-Way Audio

To use two-way audio, open the live view in the Home app and tap the microphone icon to speak. Tap again to mute.

### 4.3 Privacy Features

Your Circle View camera offers two methods for immediate privacy:

- **Physical Tilt:** Manually tilt the camera lens downwards towards its base to obscure its view.
- **On/Off Button:** Press the button located on the rear of the camera to instantly power it off.



**DISEÑADA PARA TU PRIVACIDAD**  
**Inclina la cámara hacia abajo para ocultarte de la vista**

**Image Description:** A hand is shown gently tilting the Logitech Circle View camera's lens downwards, demonstrating its physical privacy feature.



## APAGA CON SÓLO PULSAR UN BOTÓN

**Image Description:** A hand is shown pressing the power button located on the back of the Logitech Circle View camera, indicating the method for turning the device off.

### 5. MAINTENANCE

---

- **Cleaning:** Use a soft, dry cloth to clean the camera lens and body. Avoid abrasive cleaners or solvents.
- **Firmware Updates:** Ensure your camera's firmware is up to date through the Apple Home app to benefit from the latest features and security enhancements.
- **Environmental Considerations:** While weatherproof, avoid prolonged exposure to extreme temperatures or direct, high-pressure water jets.

### 6. TROUBLESHOOTING

---

#### 6.1 Camera Offline / Connectivity Issues

- **Check Wi-Fi:** Ensure your home Wi-Fi network is operational and the camera is within range of a strong signal. Weak Wi-Fi is a common cause of disconnections.

- **Power Cycle:** Unplug the camera's power adapter, wait 10 seconds, and plug it back in.
- **Restart Home Hub:** Restart your Apple HomeKit home hub (Apple TV, HomePod).
- **Router Settings:** Verify your router settings are compatible with HomeKit devices. Consult your router's manual or ISP if necessary.

## 6.2 HomeKit Pairing Failure

- **Reset Camera:** If the camera fails to pair, perform a factory reset. Refer to the camera's specific reset procedure (often involves holding a button for several seconds).
- **Verify HomeKit Code:** Ensure you are scanning the correct HomeKit setup code.
- **iOS Device and Home Hub:** Confirm your iOS device and HomeKit home hub are updated to the latest software versions.

## 6.3 Poor Video Quality

- **Clean Lens:** Ensure the camera lens is clean and free from smudges or dirt.
- **Wi-Fi Bandwidth:** Check your internet speed and Wi-Fi bandwidth. High-definition streaming requires sufficient bandwidth.
- **Lighting:** While the camera has night vision, extreme lighting conditions can affect video clarity.

## 7. SPECIFICATIONS

---





# DIMENSIONES

**Image Description:** A diagram illustrating the physical dimensions of the Logitech Circle View camera: 6.72 cm width, 5.68 cm height, and 7.05 cm depth. The camera weighs 255 grams.

Feature	Detail
Model Number	961-000489-cr
Video Resolution	1080p HD
Field of View	180 Degrees
Night Vision	Infrared, up to 15ft
Connectivity	Wi-Fi (2.4 GHz), USB
Power Source	Corded Electric
Weatherproof Rating	IP64
Controller Type	Apple HomeKit






Feature	Detail
Dimensions (L x W x H)	5.69 x 6.72 x 7.05 inches
Item Weight	9 ounces (255 grams)
Color	Graphite
Material	Metal

## 8. WARRANTY AND SUPPORT

This product is offered as an Amazon Renewed item. Amazon Renewed products are professionally inspected and tested to work and look like new. If you are not satisfied with your purchase, renewed products are eligible for replacement or refund under the [Amazon Renewed Guarantee](#).

For further assistance or technical support, please refer to the Apple Home app's help section or visit the Logitech support website.

### Related Documents - 961-000489-cr

	<a href="#">Logitech Circle View Doorbell: Electrical Compatibility and Getting Started</a> Information on the electrical compatibility and installation requirements for the Logitech Circle View Doorbell, including system voltage, Wi-Fi, and Apple HomeKit Secure Video.
	<a href="#">Logitech Circle View Wired Doorbell Installation and Reset Guide</a> Comprehensive guide for installing and performing a hardware reset on the Logitech Circle View Wired Doorbell, including setup instructions for Apple HomeKit.
	<a href="#">Logitech Circle View Wired Doorbell Installation and Safety Guide</a> Comprehensive guide for installing and safely using the Logitech Circle View Wired Doorbell, including setup options, hardware reset instructions, and important safety information.
	<a href="#">Logitech Circle View Wired Doorbell Installation and Reset Guide</a> A concise guide to installing and performing a hardware reset on the Logitech Circle View Wired Doorbell, including setup instructions and Apple HomeKit compatibility.
	<a href="#">Logitech Circle View Wired Doorbell: Installation and Hardware Reset Guide</a> Comprehensive guide for installing and performing a hardware reset on the Logitech Circle View Wired Doorbell. Includes setup instructions, Apple HomeKit compatibility, and troubleshooting steps.



## [Logitech Circle View Camera: Setup, Mounting, and Safety Guide](#)

A concise guide to setting up, mounting, and safely operating your Logitech Circle View Camera, including essential safety, compliance, and warranty information.