

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

> [Goreit](#) /

> [Goreit Flashlights High Lumens Rechargeable, 2000 Lumen XHP70.2 LED Flashlight USB Super Bright Flash Lights, High Powered Handheld Flashlights for Emergencies Camping, Waterproof, Adjustable Focus 1.5](#)

Goreit US-G9322

Goreit G9322 XHP70.2 LED Flashlight Instruction Manual

Model: US-G9322

PRODUCT OVERVIEW

The Goreit G9322 is a high-performance, rechargeable LED flashlight designed for various applications including emergencies, camping, hiking, fishing, and general household use. Featuring an upgraded XHP70.2 LED chip, it delivers a powerful 2000 lumens, illuminating distances up to 753.2 feet. Its robust aluminum alloy construction ensures durability and IP67 waterproofing, making it suitable for harsh environments.



Image: The Goreit G9322 flashlight showcasing its powerful beam in a dark outdoor environment, highlighting its super bright and long-range capabilities.

WHAT'S IN THE BOX

Upon unboxing your Goreit G9322 flashlight, you will find the following components:

- 1 x Goreit Rechargeable Flashlight
- 1 x USB Charging Cable
- 1 x Lanyard
- 1 x Operating Instructions



Image: A visual representation of all items included in the Goreit G9322 product package.

SETUP

Battery Installation

The Goreit G9322 flashlight uses a rechargeable Lithium Polymer battery. Before first use, ensure the battery is correctly installed and fully charged.

1. Unscrew the rear cover of the flashlight.
2. Remove any transparent plastic protective film from the battery surface.
3. Insert the battery with the positive (+) end facing towards the head of the flashlight.
4. Screw the rear cover back on securely.



Image: Step-by-step guide for proper battery insertion into the flashlight.

Initial Charging

For optimal performance, fully charge the flashlight before its first use. The built-in USB interface allows for convenient charging.

- Locate the USB charging port on the side of the flashlight (under a protective cover).
- Connect the provided USB charging cable to the flashlight's port and to a USB power source (e.g., AC adapter, car

charger, computer, power bank).

- The indicator light on the switch will turn red while charging. It will turn green when fully charged.



Image: Illustration of the USB input and output features, including charging status indicators.

OPERATING INSTRUCTIONS

Power On/Off

To prevent accidental activation and battery drain, the flashlight features an improved switch design:

- To turn the flashlight **ON**, press and hold the power button for 3 seconds.
- To turn the flashlight **OFF**, press and hold the power button for 3 seconds again.

Your browser does not support the video tag.

Video: Official demonstration of the Goreit G9322 flashlight's power on/off mechanism, requiring a 3-second press to activate or deactivate.

Light Modes

The Goreit G9322 offers 5 distinct lighting modes:

1. **High:** Maximum brightness for powerful illumination.
2. **Medium:** Balanced brightness for general use.
3. **Low:** Reduced brightness for extended runtime or close-up tasks.
4. **Strobe:** Flashing light for signaling or disorienting.
5. **SOS:** International Morse code signal for emergencies.

To cycle through the modes, briefly press the power button while the flashlight is on.



Image: Visual representation of the five available light modes and the adjustable focus feature.

Adjustable Focus

The flashlight features an adjustable focus mechanism to switch between a wide floodlight and a concentrated spotlight:

- To adjust the beam, gently slide the head of the flashlight forward or backward.
- Sliding forward narrows the beam for a focused spotlight.
- Sliding backward widens the beam for a broad floodlight.

USB Input & Output



Image: The adjustable focus feature, illustrating the transition from a wide floodlight to a narrow spotlight beam.

USB Input | USB Output (Power Bank Function)

Beyond charging the flashlight itself, the Goreit G9322 can also serve as a power bank to charge other electronic devices.

- To charge the flashlight, use the USB input port (Type-C).
- To charge another device, connect your device's USB cable to the flashlight's USB output port. The flashlight must be turned on for this function to work.

SUPER BRIGHT & LONG RANGE

2000 Lumens



Image: Detailed view of the USB input and output ports, demonstrating how to charge the flashlight and use it as a power bank for other devices.

MAINTENANCE

Waterproofing and Durability

The Goreit G9322 is built for rugged use:

- **IP67 Waterproof:** This rating means the flashlight is protected from dust and can withstand temporary immersion in water (up to 1 meter for 30 minutes). Ensure the USB port cover is securely closed to maintain waterproofing.
- **Practically Indestructible:** Constructed from aerospace-grade aluminum alloy, it is designed to endure drops and harsh conditions.

IP67 Waterproof Tactical Flashlight



Image: The flashlight shown in a wet environment, emphasizing its IP67 waterproof and robust design.

Battery Care

To prolong battery life and ensure consistent performance:

- Charge the battery when the indicator light turns red.
- Avoid completely draining the battery, as this can reduce its lifespan.
- Store the flashlight in a cool, dry place when not in use for extended periods.

TROUBLESHOOTING

Problem	Possible Cause	Solution
Flashlight does not turn on.	Battery is low or dead; Incorrect power button press; Battery not installed correctly.	Charge the battery; Press and hold the power button for 3 seconds; Ensure battery is inserted with correct polarity.

Problem	Possible Cause	Solution
Light output is dim.	Low battery charge; Lens is dirty.	Recharge the battery; Clean the lens with a soft cloth.
Flashlight gets hot on high mode.	Normal operation for high lumen output.	Reduce brightness to medium or low mode if prolonged use is required.
Cannot charge other devices.	Flashlight is off; Cable is incompatible; Device is not compatible.	Turn on the flashlight; Use the provided USB cable or a compatible one; Ensure your device supports USB charging from a power bank.

SPECIFICATIONS

Feature	Detail
Brand	Goreit
Model Number	US-G9322
Light Source Type	XHP70.2 LED Chip
Brightness	2000 Lumens
Light Path Distance	753.2 Feet
Light Modes	High, Medium, Low, Strobe, SOS (5 modes)
Battery Type	1 Lithium Polymer battery required (5000mAh)
Runtime (Low Mode)	Up to 10 hours
Charging Interface	USB Type-C (Input)
Output Interface	USB (Output for charging other devices)
Material	Aerospace Grade Aluminum Alloy
Water Resistance	IP67 Waterproof
Product Dimensions	7.09"D x 1.18"W x 1.69"H
Item Weight	11.99 ounces

WARRANTY & SUPPORT

Goreit offers 7*24-hour customer service for any questions or concerns regarding your G9322 flashlight. Please do not hesitate to contact us for assistance.