**Saved from manuals.plus.**
**Open the live page for links to other documents and user manuals.**



### Giaomar C9

# Giaomar Native 1080P Full HD Projector User Manual

Model: C9

## 1. Introduction

Thank you for purchasing the Giaomar Native 1080P Full HD Projector. This manual provides essential information for setting up, operating, and maintaining your projector to ensure optimal performance and longevity. Please read this manual thoroughly before using the product and retain it for future reference.

## 2. What's in the Box

- Projector Unit
- Customized Carrying Case
- AV Signal Cable
- Remote Control
- Power Plug
- User Manual

## 3. Product Overview

The Giaomar C9 Projector is a portable, high-brightness device designed for home cinema and outdoor movie experiences. It features native 1080P resolution with 4K support, 8500 lumens brightness, and a 10000:1 contrast ratio. It includes built-in dual stereo speakers and offers various connectivity options.




This image displays the Giaomar projector from the front, showcasing its lens and ventilation. The compact design highlights its portability.

# 4. Setup

## 4.1. Placement

Place the projector on a stable, flat surface. Ensure there is adequate ventilation around the unit. For optimal viewing, position the projector directly in front of the screen or wall. The recommended projection distance is 1.5m to 3m for a screen size of 50 to 100 inches.

## 4.2. Power Connection

Connect the provided power cable to the projector's power input port and then plug it into a standard electrical outlet.

## 4.3. Focus and Keystone Correction

Adjust the focus ring on the projector lens until the projected image is clear. Use the keystone correction feature (if available, typically via remote or a physical dial) to correct any trapezoidal distortion, ensuring a rectangular image.

# 5. Operating Instructions

## 5.1. Power On/Off

Press the power button on the projector or the remote control to turn the unit on or off. Allow a few seconds for the projector to warm up or cool down.

## 5.2. Input Source Selection

Use the 'Source' button on the remote control or projector to cycle through available input options: HDMI, USB, AV, VGA, and TF Card. Select the input corresponding to your connected device.

## 5.3. Wireless Connectivity (WiFi)

The projector supports WiFi connection for screen mirroring from iOS and Android devices. There are two methods:

1. **Same WiFi Network:** Connect both the projector and your smartphone to the same WiFi network. Then, select the screen mirror function on your phone (for iOS, choose 'Screen Mirroring' not 'AirPlay'). This allows for streaming video content over WiFi.
2. **Projector Hotspot:** Directly connect your phone to the projector's built-in hotspot. This method enables screen mirroring even in environments without an external WiFi network.

*Note: Due to copyright restrictions, some protected videos on platforms like Netflix, Amazon Prime Video, and Hulu may not support the mirror display function.*




The projector displaying content mirrored from a smartphone, highlighting its wireless connectivity capabilities.

### 5.4. Bluetooth Connectivity

The projector supports Bluetooth connectivity, allowing you to connect external Bluetooth audio devices for an enhanced sound experience.

### 5.5. Adjusting Image Size (Zoom Function)

The projector features a zoom function that allows you to shrink the image size from 100% to 50% using the remote control, without needing to physically move the projector.

### 5.6. Audio Output

The projector is equipped with built-in 3W dual stereo speakers with an SRS sound system, providing a clear audio experience. External speakers can also be connected if desired.

## 6. Usage Scenarios

The Giaomar projector is versatile and suitable for various entertainment settings:



An outdoor setup showing the projector used for a movie night during camping, demonstrating its portability and suitability for outdoor entertainment.




A group of people enjoying a football game projected onto a large screen in a home living room, illustrating the home cinema experience.

# 7. Maintenance

## 7.1. Cleaning the Lens

Use a soft, lint-free cloth specifically designed for optical lenses to gently wipe the projector lens. Avoid using abrasive materials or harsh chemicals that could scratch or damage the lens.

### 7.2. Cleaning Ventilation

Regularly check and clean the projector's ventilation ports to prevent dust buildup, which can affect performance and lead to overheating. Use a soft brush or compressed air to clear any obstructions.

### 7.3. Storage

When not in use, store the projector in a cool, dry place, away from direct sunlight and extreme temperatures. Use the provided carrying case for protection during storage and transport.

## 8. Troubleshooting

### 8.1. No Image Displayed

- Ensure the power cable is securely connected and the projector is turned on.
- Verify that the correct input source is selected (HDMI, USB, AV, etc.).
- Check the connection cable between the projector and the source device (e.g., HDMI cable).
- Adjust the focus and keystone correction.

### 8.2. No Sound

- Check the volume settings on both the projector and the source device.
- Ensure that any external audio devices are properly connected and powered on.
- If using HDMI, verify that the audio output is correctly configured on the source device.

### 8.3. Wireless Connection Issues

- Ensure both devices are connected to the same WiFi network or that your phone is connected to the projector's hotspot.
- Restart both the projector and your mobile device.
- Check for any firewall or network restrictions that might be blocking the connection.

## 9. Specifications

| Feature | Detail |
|---|---|
| Brand | Giaomar |
| Model Number | C9 |
| Display Resolution | Native 1920 x 1080P (4K Supported) |
| Brightness | 8500 Lumens |
| Contrast Ratio | 10000:1 |
| Aspect Ratio | 16:9 / 4:3 |
| Projection Distance | 1.5m - 3m |
| Screen Size | 50 - 100 inches |
| Connectivity Technology | Bluetooth, HDMI, USB, Wi-Fi |

| | |
|---|---|
| Built-in Speaker | 3W Dual Stereo Speakers with SRS Sound System |
| Item Weight | 4.4 pounds |
| Product Dimensions | 0.39 x 0.39 x 0.39 inches |
| Color | Pink |

## 10. Warranty & Support

The Giaomar projector comes with a 6-month return policy and a 3-year repair warranty. Lifetime professional technical support is also provided. For any inquiries or assistance, please refer to the 'Contact us' option within the projector's menu interface or reach out to the seller directly through your purchase platform.

© 2023 Giaomar. All rights reserved.

### Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

**Name**

Anonymous

**Email**

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

**Question**

Example: How do I reset this device or fix this error?

**Details**

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

**Open the live page**

**https://manuals.plus/asin/B09YT1Z9SM**

More documents and user manuals: **https://manuals.plus/**